



AXIS Q6088-E PTZ Camera - User manual

[← GO TO AXIS DOCUMENTATION](#)

▼ Installation

Preview mode

- Get started
- Configure your device

Configuration

- The web interface
- Learn more
- Specifications

Clean your device

- Troubleshooting


Installation

Preview mode

Preview mode is ideal for installers when fine tuning the camera view during the installation. No login is required to access the camera view in preview mode. It is available only in factory defaulted state for a limited time from powering up the device.



AXIS Q6088-E PTZ Camera - User manual



This video demonstrates how to use preview mode.

Get started

Find the device on the network

To find Axis devices on the network and assign them IP addresses in Windows®, use AXIS IP Utility or AXIS Device Manager. Both applications are free and can be downloaded from axis.com/support.

For more information about how to find and assign IP addresses, go to [How to assign an](#)



AXIS Q6088-E PTZ Camera - User manual

browsers:

	Chro me™	Edge ^T M	Firefo x®	Safari ®
Windo ws®	✓	✓	*	*
macOS ®	✓	✓	*	*
Linux ®	✓	✓	*	*
Other operat ing syste ms	*	*	*	*

✓: Recommended
*: Supported with limitations

Open the device's web interface

1. Open a browser and type the IP address or host name of the Axis device.
If you do not know the IP address, use AXIS IP Utility or AXIS Device Manager to find the device on the network.
2. Type the username and password. If you access the device for the first time, you must create an administrator account.
See [Create an administrator account](#).



AXIS Q6088-E PTZ Camera - User manual

Create an administrator account

The first time you log in to your device, you must create an administrator account.

1. Enter a username.
2. Enter a password. See [Secure passwords](#).
3. Re-enter the password.
4. Accept the license agreement.
5. Click **Add account**.

Important

The device has no default account. If you lose the password for your administrator account, you must reset the device. See [Reset to factory default settings](#).

Secure passwords

Important

Use HTTPS (which is enabled by default) to set your password or other sensitive configurations over the network. HTTPS enables secure and encrypted network connections, thereby protecting sensitive data, such as passwords.

The device password is the primary protection for your data and services. Axis devices do not impose a password policy as they may be used in various types of installations.



AXIS Q6088-E PTZ Camera - User manual

password generator.

Don't expose the password.

Change the password at a recurring interval, at least once a year.

Make sure that no one has tampered with the device software

To make sure that the device has its original AXIS OS, or to take full control of the device after a security attack:

1. Reset to factory default settings. See [Reset to factory default settings](#).
After the reset, secure boot guarantees the state of the device.
2. Configure and install the device.

Configure your device

This section covers all the important configurations that an installer needs to do to get the product up and running after the hardware installation has been completed.

Basic settings

Set the capture mode

1. Go to Video > Installation > Capture mode.
2. Click Change.



AXIS Q6088-E PTZ Camera - User manual

Set the power line frequency

1. Go to **Video > Installation > Power line frequency**.
2. Click **Change**.
3. Select a power line frequency and click **Save and restart**.

Set the orientation

1. Go to **Video > Installation > Rotate**.
2. Select **0** or **180** degrees.

Adjust the image

This section includes instructions about configuring your device. If you want to learn more about how certain features work, go to [Learn more](#).

Level the camera

To adjust the view in relation to a reference area or an object, use the level grid in combination with a mechanical adjustment of the camera.

1. Go to **Video > Image >** and click .
2. Click  to show the level grid.
3. Adjust the camera mechanically until the position of the reference area or the object is aligned with the level grid.

Adjust the focus

This product can have four focus modes:


Auto: The camera automatically adjusts



AXIS Q6088-E PTZ Camera - User manual

Manual: The focus is set manually at a fixed distance.

Spot: The focus is set to a fixed area in the center of the image.



Spot focus

To turn off autofocus and adjust the focus manually:

1. In the live view window, if the **Zoom** slider is visible, click **Zoom** and select **Focus**.
2. Click

and use the slider to set the focus.

Select scene profile

A scene profile is a set of predefined image appearance settings including color level, brightness, sharpness, contrast and local contrast. Scene profiles are preconfigured in the product for quick setup to a specific scenario, for example **Forensic** which is optimized for surveillance conditions. For a description of each available setting, see [The web interface](#).

You can select a scene profile during the initial setup of the camera. You can also



AXIS Q6088-E PTZ Camera - User manual

Reduce image processing time with low latency mode

You can optimize the image processing time of your live stream by turning on low latency mode. The latency in your live stream is reduced to a minimum. When you use low latency mode, the image quality is lower than usual.

1. Go to **System > Plain config**.
2. Select **ImageSource** from the drop-down list.
3. Go to **ImageSource/I0/Sensor > Low latency mode** and select **On**.
4. Click **Save**.

Select exposure mode

To improve image quality for specific surveillance scenes, use exposure modes. Exposure modes lets you control aperture, shutter speed, and gain. Go to **Video > Image > Exposure** and select between the following exposure modes:

Benefit from IR light in low-light conditions by using night mode

Your camera uses visible light to deliver color images during the day. But as the visible light diminishes, color images become less bright and clear. If you switch to night mode when this happens, the camera uses both visible and near-infrared light to deliver bright and detailed black-and-white images instead. You can set the camera to switch to night mode automatically.



AXIS Q6088-E PTZ Camera - User manual

camera to switch to night mode, move the **Threshold** slider toward **Bright** or **Dark**.

Note

If you set the switch to night mode to occur when it's brighter, the image remains sharper as there is less low-light noise. If you set the switch to occur when it's darker, the image colors are maintained for longer, but there is more image blur due to low-light noise.

Reduce noise in low-light conditions

To reduce noise in low-light conditions, you can adjust one or more of the following settings:

Adjust the trade-off between noise and motion blur. Go to **Video > Image > Exposure** and move the **Blur-noise trade-off** slider toward **Low noise**.

Note

A high max shutter value can result in motion blur.

To slow down the shutter speed, set max shutter to the highest possible value.

Note



AXIS Q6088-E PTZ Camera - User manual

Set the max gain to a lower value.

If there is an **Aperture** slider, move it towards **Open**.

Reduce motion blur in low-light conditions

To reduce motion blur in low-light conditions, adjust one or more of the following settings in **Video > Image > Exposure**:

Note

When you increase the gain, image noise also increases.

Set **Max shutter** to a shorter time, and **Max gain** to a higher value.

If you still have problems with motion blur:

Increase the light level in the scene.

Mount the camera so that objects move toward it or away from it rather than sideways.

Maximize the details in an image

Important

If you maximize the details in an image, the bitrate will probably increase and you might get a reduced frame rate.

Make sure to select the capture mode that has the highest resolution.



AXIS Q6088-E PTZ Camera - User manual

and in **Video** format, select **MJPEG**.

Go to **Video > Stream > Zipstream** and select **Off**.

Handle scenes with strong backlight

Dynamic range is the difference in light levels in an image. In some cases the difference between the darkest and the brightest areas can be significant. The result is often an image where either the dark or the bright areas are visible. Wide dynamic range (WDR) makes both dark and bright areas of the image visible.

1. Go to **Video > Image > Wide dynamic range**.
2. Use the **Local contrast** slider to adjust the amount of WDR.
3. Use the **Tone mapping** slider to adjust the amount of WDR.
4. If you still have problems, go to **Exposure** and adjust the **Exposure zone** to cover the area of interest.

Find out more about WDR and how to use it at [axis.com/web-articles/wdr](https://help.axis.com/en-us/axis-q6088-e/web-articles/wdr).

Stabilize a shaky image with image stabilization



AXIS Q6088-E PTZ Camera - User manual

The feature makes the image smoother, steadier, and less blurry. It also reduces the file size of the compressed image and lowers the bitrate of the video stream.

Note

When you turn on image stabilization, the image is slightly cropped, which lowers the maximum resolution.

1. Go to **Video > Installation > Image correction**.
2. Turn on **Image stabilization**.

Compensate for barrel distortion

Barrel distortion is a phenomenon where straight lines appear increasingly bent closer to the edges of the frame. A wide field of view often creates barrel distortion in an image. Barrel distortion correction compensates for this distortion.

Note

Barrel distortion correction affects the image resolution and field of view.

1. Go to **Video > Installation > Image correction**.
2. Turn on **Barrel distortion correction (BDC)**.

Verify the pixel resolution



AXIS Q6088-E PTZ Camera - User manual

1. Go to **Video > Image**.
2. Click

3. Click

for **Pixel counter**.

4. In the camera's live view, adjust the size and position of the rectangle around the area of interest, for example where you expect license plates to appear.
5. You can see the number of pixels for each of the rectangle's sides, and decide if the values are enough for your needs.

Hide parts of the image with privacy masks

You can create one or several privacy masks to hide parts of the image.



AXIS Q6088-E PTZ Camera - User manual

3. Click the new mask and type a name.
 4. Adjust the size and placement of the privacy mask according to your needs.
 5. To change the color for all privacy masks, click **Privacy masks** and select a color.
- See also [Privacy masks](#)

Show an image overlay

You can add an image as an overlay in the video stream.

1. Go to **Video > Overlays**.
2. Click **Manage images**.
3. Upload or drag and drop an image.
4. Click **Upload**.
5. Select **Image** from the drop-down list and click

6. Select the image and a position. You can also drag the overlay image in the live view to change the position.

Show a text overlay

You can add a text field as an overlay in the video stream. This is useful for example



AXIS Q6088-E PTZ Camera - User manual

2. Select text and click

3. Type the text you want to display, or select modifiers to show for example the current date.
4. Select a position. You can also click-and-drag the overlay in the live view to change the position.

Show the pan or tilt position as a text overlay

You can show the pan or tilt position as an overlay in the image.

1. Go to **Video > Overlays** and click
2. In the text field, type #x to show the pan position.
Type #y to show the tilt position.
3. Choose appearance, text size, and alignment.
4. The current pan and tilt positions show up in the live view image and in the recording.



AXIS Q6088-E PTZ Camera - User manual

The preset positions and compass direction will be visible in the compass field in all video streams and recordings.

To activate the compass:

1. Go to **PTZ > Orientation aid**.
2. Turn on **Orientation aid**.
3. Position the camera view at north with the crosshair. Click **Set north**.

To add a preset position to show in the compass field:

1. Go to **PTZ > Preset positions**.
2. Use the crosshair to position the view where you want to add a preset position.
3. Click

Add preset position to create a new preset position.

Adjust the camera view (PTZ)

Limit the pan, tilt, and zoom movements

If there are parts of the scene that you don't want the camera to reach, you can limit the pan, tilt, and zoom movements. For



AXIS Q6088-E PTZ Camera - User manual

To limit the movements:

1. Go to **PTZ > Limits**.
2. Set the limits as needed.

Create a guard tour with preset positions

A guard tour displays the video stream from different preset positions either in a predetermined or random order, and for configurable periods of time.

1. Go to **PTZ > Guard tours**.
2. Click

Guard tour.

3. Select **Preset position** and click **Create**.
4. Under **General settings**:

Enter a name for the guard tour and specify the pause length between each tour.

If you want the guard tour to go to the preset positions in a random order, turn on **Play guard tour in random order**.

5. Under **Step settings**:

Set the duration for the preset.

Set the move speed, which controls how fast to move to the next preset.



AXIS Q6088-E PTZ Camera - User manual

and click **Done**.

7. To schedule the guard tour, go to **System > Events**.

Create a recorded guard tour

1. Go to **PTZ > Guard tours**.
2. Click

Guard tour.

3. Select **Recorded** and click **Create**.
4. Enter a name for the guard tour and specify the pause length between each tour.
5. Click **Start recording tour** to start recording the pan/tilt/zoom movements.
6. When you're satisfied, click **Stop recording tour**.
7. Click **Done**.
8. To schedule the guard tour, go to **System > Events**.

View and record video

This section includes instructions about configuring your device. To learn more about how streaming and storage works, go to [Streaming and storage](#).

Reduce bandwidth and storage



AXIS Q6088-E PTZ Camera - User manual

1. Go to **Video > Stream**.
2. Click

in the live view.

3. Select **Video format AV1** if your device supports it. Otherwise select **H.264**.
4. Go to **Video > Stream > General** and increase **Compression**.
5. Go to **Video > Stream > Zipstream** and do one or more of the following:

Note

The **Zipstream** settings are used for all video encodings except MJPEG.

Select the Zipstream **Strength** that you want to use.

Turn on **Optimize for storage**. This can only be used if the video management software supports B-frames.

Turn on **Dynamic FPS**.

Turn on **Dynamic GOP** and set a high **Upper limit** GOP length value.

Note



AXIS Q6088-E PTZ Camera - User manual

management system or application that supports H.265 decoding.

Set up network storage

To store recordings on the network, you need to set up your network storage.

1. Go to **System > Storage**.
2. Click

Add network storage under **Network storage**.

3. Type the IP address of the host server.
4. Type the name of the shared location on the host server under **Network share**.
5. Type the username and password.
6. Select the SMB version or leave it on **Auto**.
7. Select **Add share without testing** if you experience temporary connection issues, or if the share is not yet configured.
8. Click **Add**.

Record and watch video

Record video directly from the camera

1. Go to **Video > Stream**.



AXIS Q6088-E PTZ Camera - User manual

If you haven't set up any storage, click

and

For instructions on how to set up network storage, see [Set up network storage](#)

3. To stop recording, click

again.

Watch video

1. Go to **Recordings**.



AXIS Q6088-E PTZ Camera - User manual

for your recording in the list.

Verify that no one has tampered with the video

With signed video, you can make sure that no one has tampered with the video recorded by the camera.

1. Go to **Video > Stream > General** and turn on **Signed video**.
2. Use AXIS Camera Station (5.46 or later) or another compatible video management software to record video. For instructions, see the [AXIS Camera Station user manual](#).
3. Export the recorded video.
4. Use AXIS File Player to play the video. [Download AXIS File Player](#).

indicates that no one has tampered with the video.

Note

To get more information about the video, right-click the video and select **Show digital signature**.



AXIS Q6088-E PTZ Camera - User manual

pair the camera with a radar and use the camera to configure and maintain both devices. The camera has an allocated channel for the radar stream, and after pairing the radar stream will be automatically assigned to this channel.

To learn more about edge-to-edge, see [Edge-to-edge technology](#).

Before you start:

Make sure the camera and radar are directed towards the same area of interest.

Make sure the camera and radar are synced to the same time source. To check the time sync status, go to **Installation > Time sync status** in each device.

Pair the camera with the radar:

1. In the camera's web interface, go to **System > Edge-to-edge > Pairing**.
2. Click

Add and select the pairing type **Radar** from the drop-down list.

3. Enter the host name, user name, and password of the radar.
4. Click **Connect** to pair the devices.
When the connection is established, the radar settings will be available in the



AXIS Q6088-E PTZ Camera - User manual

radar is 1280x720. Keep the radar's default resolution in the camera's web interface, and if you add it to a VMS.

Configure the radar:

1. In the camera's web interface, go to **Radar > Scenarios**.
2. Configure the radar according to your needs.

For more information about how to configure your radar, see the user manual at help.axis.com.

Note

When you upgrade the AXIS OS version for the camera, make sure to also upgrade AXIS OS for the radar to keep your system up-to-date. We recommend using a device management system like AXIS Device Manager.

Set up rules for events

You can create rules to make your device perform an action when certain events occur. A rule consists of conditions and actions. The conditions can be used to trigger the actions. For example, the device can start a recording or send an email when it detects motion, or show an overlay text while the device is recording.

To learn more, check out our guide [Get started with rules for events](#).



AXIS Q6088-E PTZ Camera - User manual

rules as scheduled, recurring, or manually triggered.

2. Enter a **Name**.
3. Select the **Condition** that must be met to trigger the action. If you specify more than one condition for the rule, all of the conditions must be met to trigger the action.
4. Select which **Action** the device should perform when the conditions are met.

Note

If you make changes to an active rule, the rule must be turned on again for the changes to take effect.

Record video when the camera detects an object

This example explains how to set up the camera to start recording to the SD card when the camera detects an object. The recording will include five seconds before detection and one minute after detection ends.

Before you start:

Make sure you have an SD card installed.

Make sure that AXIS Object Analytics is running:

1. Go to **Apps > AXIS Object Analytics**.
2. Start the application if it is not already running.



AXIS Q6088-E PTZ Camera - User manual

2. Type a name for the rule.
3. In the list of conditions, under **Application**, select **Object Analytics**.
4. In the list of actions, under **Recordings**, select **Record video while the rule is active**.
5. In the list of storage options, select **SD_DISK**.
6. Select a camera and a stream profile.
7. Set the prebuffer time to 5 seconds.
8. Set the postbuffer time to 1 minute.
9. Click **Save**.

Show a text overlay in the video stream when the device detects an object

This example explains how to display the text "Motion detected" when the device detects an object.

Make sure that AXIS Object Analytics is running:

1. Go to **Apps > AXIS Object Analytics**.
2. Start the application if it is not already running.
3. Make sure you have set up the application according to your needs.

Add the overlay text:

1. Go to **Video > Overlays**.



AXIS Q6088-E PTZ Camera - User manual

3. Enter #D in the text field.
4. Choose text size and appearance.
5. To position the text overlay, click

and select an option.

Create a rule:

1. Go to **System > Events** and add a rule.
2. Type a name for the rule.
3. In the list of conditions, under **Application**, select **Object Analytics**.
4. In the list of actions, under **Overlay text**, select **Use overlay text**.
5. Select a video channel.
6. In **Text**, type "Motion detected".
7. Set the duration.
8. Click **Save**.

Note

If you update the overlay text it will be automatically updated on all video streams dynamically.



AXIS Q6088-E PTZ Camera - User manual

camera to go to a preset position when it detects motion in the image.

Make sure that AXIS Object Analytics is running:

1. Go to **Apps > AXIS Object Analytics**.
2. Start the application if it is not already running.
3. Make sure you have set up the application according to your needs.

Add a preset position:

Go to **PTZ** and set where you want the camera to be directed by creating a preset position.

Create a rule:

1. Go to **System > Events** and add a rule.
2. Type a name for the rule.
3. In the list of conditions, under **Application**, select **Object Analytics**.
4. In the list of actions, select **Go to preset position**.
5. Select the preset position you want the camera to go to.
6. Click **Save**.

Record video when the camera detects impact

Shock detection allows the camera to detect tampering caused by vibrations or shock. Vibrations due to the environment or to an object can trigger an action depending on the shock sensitivity range, which can be set from 0 to 100. In this scenario, someone is



AXIS Q6088-E PTZ Camera - User manual

1. Go to **System > Detectors > Shock detection**.
2. Turn on shock detection, and adjust the shock sensitivity.

Create a rule:

3. Go to **System > Events > Rules** and add a rule.
4. Type a name for the rule.
5. In the list of conditions, under **Device status**, select **Shock detected**.
6. Click + to add a second condition.
7. In the list of conditions, under **Scheduled and recurring**, select **Schedule**.
8. In the list of schedules, select **After hours**.
9. In the list of actions, under **Recordings**, select **Record video while the rule is active**.
10. Select where to save the recordings.
11. Select a **Camera**.
12. Set the prebuffer time to 5 seconds.
13. Set the postbuffer time to 50 seconds.
14. Click **Save**.

Zoom in on a specific area automatically with gatekeeper

This example explains how to use the gatekeeper functionality to make the camera zoom in automatically on the license plate of a car that passes through a gate. When the



AXIS Q6088-E PTZ Camera - User manual

1. GO TO PTZ > Preset positions.

2. Create the home position that includes the entrance of the gate.
3. Create the zoomed-in preset position so that it covers the area in the image where you assume that the license plate will appear.

Set up motion detection:

1. Go to **Apps** and start and open **AXIS Object Analytics**.
2. Create an object in area scenario for vehicles, with an include area that covers the entrance of the gate.

Create a rule:

1. Go to **System > Events** and add a rule.
2. Name the rule "Gatekeeper".
3. In the list of conditions, under **Application**, select the **Object Analytics** scenario.
4. In the list of actions, under **Preset positions**, select **Go to preset position**.
5. Select a **Video channel**.
6. Select the **Preset position**.
7. To make the camera wait a while before it returns to the home position, set a time for **Home timeout**.
8. Click **Save**.

Send an email automatically if someone spray paints the lens

This example explains how to set up a rule in the camera's web interface that sends an email when the image has been blocked for



AXIS Q6088-E PTZ Camera - User manual

Create an email recipient in the camera's web interface.

In AXIS Image Health Analytics:

1. Turn on **Blocked image**.
2. Set **Validation period** to 40 seconds.

In the camera's web interface:

3. Go to **System > Events** and add a rule.
4. Type a name for the rule.
5. In the list of conditions, under **Applications**, select **Image Health Analytics – Block**.
6. In the list of actions, under **Notifications**, select **Send notification to email**.
7. Select the recipient from the list.
8. Type a subject and message for the email.
9. Click **Save**.

Audio

Connect to a network speaker

Network speaker pairing allows you to use a compatible Axis network speaker as if it is connected directly to the camera. Once paired, the speaker acts as an audio out device where you can play audio clips and transmit sound through the camera.

Important

For this feature to work with a video management software (VMS), you must first pair the camera with the network



AXIS Q6088-E PTZ Camera - User manual

1. Go to **System > Edge-to-edge > Pairing**.
2. Click

Add and select the pairing type **Audio** from the drop-down list.

3. Select **Speaker pairing**.
4. Type the network speaker's IP address, username and password.
5. Click **Connect**. A confirmation message appears.

Set up autotracking

This example explains how to set up the camera to detect, zoom in on, and track moving objects in an area of interest.

Before you start

Make sure you have a preset position that covers the area of interest.

In AXIS Object Analytics, create a scenario that uses the preset position.

1. Go to **Analytics > Autotracking**.
2. To create a tracking profile, click **Create**.
3. In **AXIS Object Analytics scenario**, select the scenario.
4. Optionally, update the **Tracking profile name**.



AXIS Q6088-E PTZ Camera - User manual

click

and

turn on **Active**.

To show bounding boxes around objects and at the same time make it possible to manually select objects to track, turn on **Object confirmation**.

Note

It's only possible to start manual tracking from **Analytics > Autotracking**.

Configuration

The web interface

To reach the device's web interface, type the device's IP address in a web browser.

Note

Support for the features and settings described in this section varies between devices. This icon



AXIS Q6088-E PTZ Camera - User manual

Show or hide the main menu.

Access the release notes.

Access the product help.

Change the language.



AXIS Q6088-E PTZ Camera - User manual

Set light theme or dark theme.

The user menu contains:

Information about the user who is logged in.

Change account : Log out from the current account and log in to a new account.

Log out : Log out from the current account.



AXIS Q6088-E PTZ Camera - User manual

The context menu contains:

Analytics data: Accept to share non-personal browser data.

Feedback: Share any feedback to help us improve your user experience.

Legal: View information about cookies and licenses.

About: View device information, including AXIS OS version and serial number.

Status

Device info

Shows the device information, including AXIS OS version and serial number.

Upgrade AXIS OS: Upgrade the software on your device. Takes you to the Maintenance page where you can do the upgrade.

Time sync status

Shows NTP synchronization information, including if the device is in sync with an NTP server and the time remaining until the next sync.

NTP settings: View and update the NTP settings. Takes you to the **Time and**



AXIS Q6088-E PTZ Camera - User manual

Security

Shows what kind of access to the device that is active, what encryption protocols are in use, and if unsigned apps are allowed. Recommendations to the settings are based on the AXIS OS Hardening Guide.

Hardening guide: Link to [AXIS OS Hardening guide](#) where you can learn more about cybersecurity on Axis devices and best practices.

PTZ

Shows the PTZ status and the time of the last test.

Test: Start a test of the PTZ mechanics. During the test, there are no video streams available. When the test is finished, the device restores to its home position.

Power status

Shows power status information, including current power, average power, and max power.

Power settings: View and update the power settings for the device. Takes you to the Power settings page where you can change the power settings.

AXIS Image Health Analytics



AXIS Q6088-E PTZ Camera - User manual

Go to upper left to the Apps page where you can manage your installed applications.

Open application: Open AXIS Image Health Analytics in a new browser tab.

Ongoing recordings

Shows ongoing recordings and their designated storage space.

Recordings: View ongoing and filtered recordings and their source. For more information, see [Recordings](#)

Shows the storage space where the recording is saved.

Connected clients

Shows the number of connections and connected clients.



AXIS Q6088-E PTZ Camera - User manual

Video

Click-and-drag to pan and tilt in the live view.

Zoom Use the slider to zoom in and out.

Focus Use this setting to set focus in the shown area. Depending on the device, different focus modes are available.

Auto: The camera automatically adjusts focus based on the entire image.

Manual: Set the focus manually at a fixed distance.

Area: The camera automatically adjusts focus for a selected area of the image.

Spot: The camera automatically adjusts focus for the center of the image.

Brightness Use this setting to adjust the light intensity in the image, for example, to make objects easier to see. Brightness is applied after image capture, and does not affect the information in the image. To get more details in a dark area, it is



AXIS Q6088-E PTZ Camera - User manual

Click to play the live video stream.

Click to freeze the live video stream.

Click to take a snapshot of the live video stream. The file is saved in the 'Downloads' folder on your computer. The image file name is [snapshot_YYYY_MM_DD_HH_MM_SS.jpg]. The size of the snapshot depends on the compression that the specific web-browser engine where the snapshot is received applies, therefore, the snapshot size may vary from the actual compression setting that is configured in the device.



AXIS Q6088-E PTZ Camera - User manual

Click to show I/O output ports. Use the switch to open or close the circuit of a port, for example, to test external devices.

Click to manually turn on or turn off the IR illumination.



AXIS Q6088-E PTZ Camera - User manual

Click to manually turn on or turn off the white light.

Click to access onscreen controls. Enable groups of onscreen controls to make the settings in each group available when users right-click the live stream in the video management software.

Predefined controls: Lists the default onscreen controls.

Custom controls: Click

Add custom control to create customized onscreen controls.



AXIS Q6088-E PTZ Camera - User manual

Starts the washer. When the sequence starts, the camera moves to the configured position to receive the wash spray. When the whole wash sequence is completed, the camera returns to its previous position. This icon is only visible when the washer is connected and configured.

Starts the wiper.



AXIS Q6088-E PTZ Camera - User manual

Click and select a preset position to go to that preset position in the live view. Or, click **Setup** to go to the preset position page.

Adds or removes a focus recall area. When you add a focus recall area, the camera saves the focus settings at that specific pan/tilt range. When you have set a focus recall area and the camera enters that area in the live view, the camera recalls the previously saved focus. It's enough to



AXIS Q6088-E PTZ Camera - User manual

Click to select a guard tour, then click **Start** to play the guard tour. Or, click **Setup** to go to the guard tours page.

Click to manually turn on the heater for a selected period of time.

Click to start a continuous recording of the live video stream. Click again to stop the



AXIS Q6088-E PTZ Camera - User manual

Click to show the storage that is configured for the device. To configure the storage, you need to be logged in as an administrator.

Click to access autotracking settings. More settings are available if you click the icon from **Analytics > Autotracking**.

Click to access more settings:

Video format: Select the encoding format to use in the live view.



AXIS Q6088-E PTZ Camera - User manual

Autoplay: Turn on to autoplay a muted video stream whenever you open the device in a new session.

Client stream information: Turn on to show dynamic information about the video stream used by the browser that shows the live video stream. The bitrate information differs from the information shown in a text overlay, because of different information sources. The bitrate in the client stream information is the bitrate of the last second, and it comes from the encoding driver of the device. The bitrate in the overlay is the average bitrate of the last 5 seconds, and it comes from the browser. Both values cover only the raw video stream and not the additional bandwidth generated when it's transported over the network through UDP/TCP/HTTP.

Adaptive stream: Turn on to adapt the image resolution to the viewing client's actual display resolution, to improve the user experience and help prevent a possible overload of the client's hardware. The adaptive stream is only applied when you view the live video stream in the web interface in a browser. When adaptive stream is turned on, the maximum frame rate is 30 fps. If you take a snapshot while adaptive stream is turned on, it will use the



AXIS Q6088-E PTZ Camera - User manual

to show the level grid. The grid helps you decide if the image is horizontally aligned. Click

to hide it.

Pixel counter: Click

to show the pixel counter. Drag and resize the box to contain your area of interest. You can also define the pixel size of the box in the **Width** and **Height** fields.

Refresh: Click

to refresh the still image in the live view.



AXIS Q6088-E PTZ Camera - User manual

: Turn on to display PTZ controls in the live view.

Click to show the live view at full resolution. If the full resolution is larger than your screen size, use the smaller image to navigate in the image.

Click to show the live video stream in expanded full screen. Click again to exit the expanded full screen mode.

Click to show the live video stream in full screen. Press ESC to exit full screen mode.

Installation



AXIS Q6088-E PTZ Camera - User manual

A capture mode is a preset configuration that defines how the camera captures images. When you change the capture mode, it can affect many other settings, such as view areas and privacy masks.

Mounting position

The orientation of the image can change depending on how you mount the camera.

Power line frequency: To minimize image flicker, select the frequency your region uses. The American regions usually use 60 Hz. The rest of the world mostly uses 50 Hz. If you're not sure of your region's power line frequency, check with the local authorities.

Rotate: Select the preferred image orientation.

Spot focus: Use to set the focus to a fixed area in the center of the image.

Image correction



AXIS Q6088-E PTZ Camera - User manual

the same time, since it can lead to performance issues.

Barrel distortion correction (BDC)

:

Turn on to get a straighter image if it suffers from barrel distortion. Barrel distortion is a lens effect that makes the image appear curved and bent outwards. The condition is seen more clearly when the image is zoomed out.

Crop

:

Use the slider to adjust the correction level. A lower level means that the image width is kept at the expense of image height and resolution. A higher level means that image height and resolution are kept at the expense of image width.

Remove distortion

:



AXIS Q6088-E PTZ Camera - User manual

image width.

Image stabilization

:

Turn on to get a smoother and steadier image with less blur. We recommend that you use image stabilization in environments where the device is mounted in an exposed location and subject to vibrations due to, for example, wind or passing traffic.

Focal length

:

Use the slider to adjust the focal length. A higher value leads to higher magnification and a narrower angle of view, while a lower value leads to a lower magnification and a wider angle of view.

Stabilizer margin

:

Use the slider to adjust the size of the



AXIS Q6088-E PTZ Camera - User manual

is captured. If the environment has less vibration, move the slider towards **Min**.

Focus breathing correction

:

Turn on to keep the angle of view constant while you change the focus. You might not be able to zoom in as much with this function activated.

Straighten image

:

Turn on and use the slider to straighten the image horizontally by rotating and cropping it digitally. The functionality is useful when it's not possible to mount the camera exactly level. Ideally, straighten the image during installation.


:

Click to show a supporting grid in the image.



AXIS Q6088-E PTZ Camera - User manual

Click to hide the grid.



The image before and after it has been

Image

Appearance

Scene profile

:

Select a scene profile that suits your surveillance scenario. A scene profile optimizes image settings, including color level, brightness, sharpness, contrast, and local contrast, for a specific environment or purpose.

Forensic

: Suitable for surveillance purposes.



AXIS Q6088-E PTZ Camera - User manual

: Suitable for indoor environments.

Outdoor

: Suitable for outdoor environments.

Vivid

: Useful for demonstration purposes.

Traffic overview

: Suitable for vehicle traffic
monitoring.

License plate



AXIS Q6088-E PTZ Camera - User manual

grayscale image.



Contrast: Use the slider to adjust the difference between light and dark.



Brightness: Use the slider to adjust the light intensity. This can make objects easier to see. Brightness is applied after image capture, and doesn't affect the information in the image. To get more details from a dark area, it's usually better to increase gain or exposure time.



Sharpness: Use the slider to make objects in the image appear sharper by adjusting the edge contrast. If you increase the sharpness, it may increase the bitrate and the amount of storage space needed as well.



Wide dynamic range



AXIS Q6088-E PTZ Camera - User manual

Turn on to make both bright and dark areas of the image visible.

Local contrast

:

Use the slider to adjust the contrast of the image. A higher value makes the contrast higher between dark and light areas.

Tone mapping

:

Use the slider to adjust the amount of tone mapping that is applied to the image. If the value is set to zero, only the standard gamma correction is applied, while a higher value increases the visibility of the darkest and brightest parts in the image.

White balance

When the camera detects the color temperature of the incoming light, it can adjust the image to make the colors look



AXIS Q6088-E PTZ Camera - User manual

changes gradually. If the lighting changes, or when the camera is first started, it can take up to 30 seconds to adapt to the new light source. If there is more than one type of light source in a scene, that is, they differ in color temperature, the dominating light source acts as a reference for the automatic white balance algorithm. This behavior can be overridden by choosing a fixed white balance setting that matches the light source you want to use as a reference.

Light environment:

Automatic: Automatic identification and compensation for the light source color. This is the recommended setting which can be used in most situations.

Automatic – outdoors

: Automatic identification and compensation for the light source color. This is the recommended setting which can be used in most outdoor situations.



AXIS Q6088-E PTZ Camera - User manual

: Fixed color adjustment for a room with some artificial light other than fluorescent lighting and good for a normal color temperature around 2800 K.

Custom – outdoors

: Fixed color adjustment for sunny weather conditions with a color temperature around 5500 K.

Fixed – fluorescent 1: Fixed color adjustment for fluorescent lighting with a color temperature around 4000 K.

Fixed – fluorescent 2: Fixed color adjustment for fluorescent lighting with a color temperature around 3000 K.

Fixed – indoors: Fixed color adjustment for a room with some artificial light other than fluorescent lighting and good for a normal color temperature around 2800 K.

Fixed – outdoors 1: Fixed color adjustment for sunny weather conditions with a color temperature around 5500 K.



AXIS Q6088-E PTZ Camera - User manual

Street light – mercury

: Fixed color adjustment for ultraviolet emission in mercury vapor lights common in street lighting.

Street light – sodium

: Fixed color adjustment that compensates for the yellow orange color of sodium vapor lights common in street lighting.

Hold current: Keep the current settings and do not compensate for light changes.

Manual

: Fix the white balance with the help of a white object. Drag the circle to an object that you want the camera to interpret as white in the live view image. Use the **Red balance** and



AXIS Q6088-E PTZ Camera - User manual

IR-cut filter:

Auto: Select to automatically turn on and off the IR-cut filter. When the camera is in day mode, the IR-cut filter is turned on and blocks incoming infrared light, and when in night mode, the IR-cut filter is turned off and the camera's light sensitivity increases.

Note

Some devices have IR-pass filters in night mode. The IR-pass filter increases IR-light sensitivity but blocks visible light.

On: Select to turn on the IR-cut filter. The image is in color, but with reduced light sensitivity.

Off: Select to turn off the IR-cut filter. The image is in black and white for increased light sensitivity.

Threshold: Use the slider to adjust the light threshold where the camera changes from day mode to night mode.

Move the slider towards **Bright** to decrease the threshold for the IR-cut filter. The camera changes to night mode earlier.

Move the slider towards **Dark** to increase the threshold for the IR-cut



AXIS Q6088-E PTZ Camera - User manual

If your device doesn't have built-in illumination, these controls are only available when you connect a supported Axis illuminator.

Allow illumination: Turn on to let the camera use the built-in light in night mode.

Synchronize illumination: Turn on to automatically synchronize the illumination with the surrounding light. The synchronization between day and night only works if the IR-cut filter is set to **Auto** or **Off**.

Automatic illumination angle

:

Turn on to use the automatic illumination angle. Turn off to set the illumination angle manually.

Illumination angle

:

Use the slider to manually set the illumination angle, for example, if the angle needs to be different from the camera's angle of view. If the camera has a wide angle of view, you can set the illumination angle to a narrower angle,



AXIS Q6088-E PTZ Camera - User manual

:

Select the desired wavelength for the IR light.

White light

Allow illumination

:

Turn on to let the camera use white light in night mode.

Synchronize illumination

:

Turn on to automatically synchronize the white light with the surrounding light.

Exposure



AXIS Q6088-E PTZ Camera - User manual

the automatic exposure mode, of the same frequency as your power network.

Exposure mode:

Automatic: The camera adjusts the aperture, gain, and shutter automatically.

Automatic aperture

: The camera adjusts the aperture and gain automatically. The shutter is fixed.

Automatic shutter

: The camera adjusts the shutter and gain automatically. The aperture is fixed.

Hold current: Locks the current exposure settings.

Flicker-free



AXIS Q6088-E PTZ Camera - User manual

Flicker-free 50 Hz

: The camera adjusts the aperture and gain automatically, and uses the shutter speed 1/50 s.

Flicker-free 60 Hz

: The camera adjusts the aperture and gain automatically, and uses the shutter speed 1/60 s.

Flicker-reduced

: This is the same as flicker-free, but the camera might use shutter speeds faster than 1/100 s (50 Hz) and 1/120 s (60 Hz) for brighter scenes.



AXIS Q6088-E PTZ Camera - User manual

: This is the same as flicker-free, but the camera might use shutter speeds faster than 1/100 s for brighter scenes.

Flicker-reduced 60 Hz

: This is the same as flicker-free, but the camera might use shutter speeds faster than 1/120 s for brighter scenes.

Manual

: The aperture, gain, and shutter are fixed.

Exposure zone

:

Use exposure zones to optimize the exposure in a selected part of the scene,



AXIS Q6088-E PTZ Camera - User manual

The exposure zones are related to the original image (unrotated), and the names of the zones apply to the original image. This means, for example, that if the video stream is rotated 90°, then the **Upper** zone becomes the **Right** zone in the stream, and **Left** becomes **Lower**.

Automatic: Suitable for most situations.

Center: Uses a fixed area in the center of the image to calculate the exposure. The area has a fixed size and position in the live view.

Full

: Uses the entire live view to calculate the exposure.

Upper

: Uses an area with a fixed size and position in the upper part of the image to calculate the exposure.



AXIS Q6088-E PTZ Camera - User manual

: Uses an area with a fixed size and position in the lower part of the image to calculate the exposure.

Left

: Uses an area with a fixed size and position in the left part of the image to calculate the exposure.

Right

: Uses an area with a fixed size and position in the right part of the image to calculate the exposure.

Spot: Uses an area with a fixed size and position in the live view to calculate the exposure.

Custom: Uses an area in the live view to calculate the exposure. You can adjust the size and position of the area.

Max shutter: Select the shutter speed to provide the best image. Low shutter speeds (longer exposure) might cause



AXIS Q6088-E PTZ Camera - User manual

Max gain: Select the suitable max gain. If you increase the max gain, it improves the visible level of detail in dark images, but also increases the noise level. More noise can also result in increased use of bandwidth and storage. If you set the max gain to a high value, images can differ a lot if the light conditions are very different from day to night. Max gain works with max shutter to improve the image.

Motion-adaptive exposure

:

Select to reduce motion blur in low-light conditions.

Blur-noise trade-off: Use the slider to adjust the priority between motion blur and noise. If you want to prioritize low bandwidth and have less noise at the expense of details in moving objects, move the slider towards **Low noise**. If you want to prioritize the preservation of details in moving objects at the expense of noise and bandwidth, move the slider towards **Low motion blur**.

Note

You can change the exposure either by adjusting the exposure time or by adjusting the gain. If you increase the exposure time, it results in more motion blur, and if you increase the



AXIS Q6088-E PTZ Camera - User manual

exposure times over increasing gain, and the opposite if you adjust the trade-off towards **Low motion blur**. Both the gain and exposure time will eventually reach their maximum values in low-light conditions, regardless of the priority set.

Lock aperture

:

Turn on to keep the aperture size set by the **Aperture** slider. Turn off to allow the camera to automatically adjust the aperture size. You can, for example, lock the aperture for scenes with permanent light conditions.

Aperture

:

Use the slider to adjust the aperture size, that is, how much light passes through the lens. To allow more light to enter the sensor and thereby produce a brighter image in low-light conditions, move the slider towards **Open**. An open aperture also reduces the depth of field, which means that objects close to or far from the camera can appear unfocused. To



AXIS Q6088-E PTZ Camera - User manual

Defog

:

Turn on to detect the effects of foggy weather and automatically remove them for a clearer image.

Note

We recommend you not to turn on **Defog** in scenes with low contrast, large light level variations, or when the autofocus is slightly off. This can affect the image quality, for example, by increasing the contrast. Furthermore, too much light can negatively impact the image quality when defog is active.

Stream

General

Resolution: Select the image resolution suitable for the surveillance scene. A higher resolution increases bandwidth and storage.

Frame rate: To avoid bandwidth problems on the network or reduce storage size, you can limit the frame rate to a fixed



AXIS Q6088-E PTZ Camera - User manual

more bandwidth and storage capacity.

P-frames: A P-frame is a predicted image that shows only the changes in the image from the previous frame. Enter the desired number of P-frames. The higher the number, the less bandwidth is required. However, if there is network congestion, there could be a noticeable deterioration in the video quality.

Compression: Use the slider to adjust the image compression. High compression results in a lower bitrate and lower image quality. Low compression improves the image quality, but uses more bandwidth and storage when you record.

Signed video

:

Turn on to add the signed video feature to the video. Signed video protects the video from tampering by adding cryptographic signatures to the video.

Zipstream

Zipstream is a bitrate reduction technology, optimized for video surveillance, that reduces the average bitrate in an H.264, H.265, or AV1 stream in real time. Axis Zipstream applies a high bitrate in scenes where there are multiple regions of interest, for example, in scenes with moving objects.



AXIS Q6088-E PTZ Camera - User manual

Select the bitrate reduction **Strength**:

Off: No bitrate reduction.

Low: No visible quality degradation in most scenes. This is the default option and it can be used in all types of scenes to reduce the bitrate.

Medium: Visible effects in some scenes through less noise and a slightly lower level of detail in regions of lower interest, for example, where there's no movement.

High: Visible effects in some scenes through less noise and a lower level of detail in regions of lower interest, for example, where there's no movement. We recommend this level for cloud-connected devices and devices that use local storage.

Higher: Visible effects in some scenes through less noise and a lower level of detail in regions of lower interest, for example, where there's no movement.

Extreme: Visible effects in most scenes. The bitrate is optimized for smallest possible storage.

Optimize for storage: Turn on to minimize the bitrate while maintaining quality. The optimization does not apply to the stream shown in the web client. This can only be used if your VMS supports B-frames. Turning on **Optimize for storage** also turns on **Dynamic GOP**.



AXIS Q6088-E PTZ Camera - User manual

Lower limit: Enter a value to adjust the frame rate between minimal fps and the stream default fps based on scene motion. We recommend you to use lower limit in scenes with very little motion, where the fps could drop to 1 or lower.

Dynamic GOP (Group of Pictures): Turn on to dynamically adjust the interval between I-frames based on the level of activity in the scene.

Upper limit: Enter a maximum GOP length, that is, the maximum number of P-frames between two I-frames. An I-frame is a self-contained image frame that is independent of other frames.

Bitrate control

Average: Select to automatically adjust the bitrate over a longer time period and provide the best possible image quality based on the available storage.

Click to calculate the target bitrate based on available storage, retention time, and bitrate limit.



AXIS Q6088-E PTZ Camera - User manual

recordings.

Storage: Shows the estimated storage that can be used for the stream.

Maximum bitrate: Turn on to set a bitrate limit.

Bitrate limit: Enter a bitrate limit that is higher than the target bitrate.

Maximum: Select to set a maximum instant bitrate of the stream based on your network bandwidth.

Maximum: Enter the maximum bitrate.

Variable: Select to allow the bitrate to vary based on the level of activity in the scene. More activity requires more bandwidth. We recommend this option for most situations.

Overlays

:

Click to add an overlay. Select the type of overlay from the dropdown list:

Text: Select to show a text that is integrated in the live view image and visible in all views, recordings and



AXIS Q6088-E PTZ Camera - User manual

: Click to add the date modifier %F to show yyyy-mm-dd.

: Click to add the time modifier %x to show hh:mm:ss (24-hour clock).

Modifiers: Click to select any of the modifiers shown in the list to add them to the text box. For example, %a shows the day of the week.

Size: Select the desired font size.

Appearance: Select the text color and background color, for example, white text on a black background (default).

: Select the position of the overlay in the image or click and drag the



AXIS Q6088-E PTZ Camera - User manual

stream. You can use .bmp, .png, .jpeg, or .svg files.

To upload an image, click **Manage images**. Before you upload an image, you can choose to:

Scale with resolution: Select to automatically scale the overlay image to fit the video resolution.

Use transparency: Select and enter the RGB hexadecimal value for that color. Use the format RRGGBB. Examples of hexadecimal values: FFFFFFFF for white, 000000 for black, FF0000 for red, 6633FF for blue, and 669900 for green. Only for .bmp images.

Scene annotation

: Select to show a text overlay in the video stream that stays in the same position, even when the camera pans or tilts in another direction. You can choose to only show the overlay within certain zoom levels.



AXIS Q6088-E PTZ Camera - User manual

: Click to add the date modifier %F to show yyyy-mm-dd.

: Click to add the time modifier %x to show hh:mm:ss (24-hour clock).

Modifiers: Click to select any of the modifiers shown in the list to add them to the text box. For example, %a shows the day of the week.

Size: Select the desired font size.

Appearance: Select the text color and background color, for example, white text on a black background (default).

: Select the position of the overlay in the image or click and drag the overlay to move it around in the live view. The overlay is saved and remains in the pan and tilt coordinates of this position.



AXIS Q6088-E PTZ Camera - User manual

symbol that appears instead of the overlay when the camera is not within the set zoom levels.

Streaming indicator

: Select to show an animation superimposed over the video stream. The animation indicates that the video stream is live, even if the scene doesn't contain any motion.

Appearance: Select the animation color and background color, for example, red animation on a transparent background (default).

Size: Select the desired font size.

: Select the position of the overlay in the image or click and drag the overlay to move it around in the live view.



AXIS Q6088-E PTZ Camera - User manual

: Show a graph chart that displays how a measured value changes over time.

Title: Enter a title for the widget.

Overlay modifier: Select an overlay modifier as data source. If you have created MQTT overlays, they will be located at the end of the list.

: Select the position of the overlay in the image or click and drag the overlay to move it around in the live view.

Size: Select the size of the overlay.

Visible on all channels: Turn off to show only on your currently selected channel. Turn on to show on all active channels.

Update interval: Choose the time between data updates.

Transparency: Set the transparency of the entire overlay.

Background transparency: Set the transparency only of the



AXIS Q6088-E PTZ Camera - User manual

X axis

Label: Enter the text label for the x axis.

Time window: Enter how long time the data is visualized.

Time unit: Enter a time unit for the x axis.

Y axis

Label: Enter the text label for the y axis.

Dynamic scale: Turn on for the scale to automatically adapt to the data values. Turn off to manually enter values for a fixed scale.

Min alarm threshold and Max alarm threshold: These values will add horizontal reference lines to the graph, making it easier to see when the data value becomes too high or too low.

Widget: Meter

: Show a bar chart that displays the most recently measured data value.

Title: Enter a title for the widget.

Overlay modifier: Select an overlay modifier as data source. If



AXIS Q6088-E PTZ Camera - User manual

: Select the position of the overlay in the image or click and drag the overlay to move it around in the live view.

Size: Select the size of the overlay.

Visible on all channels: Turn off to show only on your currently selected channel. Turn on to show on all active channels.

Update interval: Choose the time between data updates.

Transparency: Set the transparency of the entire overlay.

Background transparency: Set the transparency only of the background of the overlay.

Points: Turn on to add a point to the graph line when data is updated.

Y axis

Label: Enter the text label for the y axis.

Dynamic scale: Turn on for the scale to automatically adapt to the data values. Turn off to manually enter values for a fixed scale.



AXIS Q6088-E PTZ Camera - User manual

it easier to see when the data value becomes too high or too low.

Privacy masks

:

Click to create a new privacy mask.

Privacy masks x/32 or Privacy masks x/100: Click this title bar to change the color of **all** privacy masks, or to delete **all** privacy masks permanently.

Cell size:

If

you choose the mosaic color, the privacy masks appear as pixilated patterns. Use the slider to change the size of the pixels.

Mask x: Click an individual mask



AXIS Q6088-E PTZ Camera - User manual

the zoom level at which it was created. Zooming out in the image hides the mask again.

Analytics

AXIS Object Analytics

Start: Click to start AXIS Object Analytics. The application will run in the background, and you can create rules for events based on the application's current settings.

Open: Click to open AXIS Object Analytics. The application opens up in a new browser tab where you can configure its settings.

Not installed: AXIS Object Analytics is not installed on this device. Upgrade AXIS OS to the latest version to get the latest version of the application.

Autotracking

Settings



AXIS Q6088-E PTZ Camera - User manual

Activate autotracking: Turn on to start tracking, automatically through enabled profiles, or manually by clicking objects in the image.

Max tracking time: Set the maximum time the camera should track an object. Turn off to keep tracking an object indefinitely.

Timeout: Set the time the camera should wait until it returns to its home position in case it loses the tracked object.

Tracking profiles

AXIS Object Analytics scenario: Select the scenario that you want to use to trigger autotracking to start. One scenario can be used only for one tracking profile. In the scenario, detection must be restricted to one preset position.

Tracking profile name: The profile name will be based on the scenario name, but you can update it if you want to.

Timeout: Set the time the camera should wait until it returns to its home position in case it loses the tracked object. This setting overrides the timeout in the Settings page.

Use profile: Turn on to enable the profile.

AXIS Image Health Analytics



AXIS Q6088-E PTZ Camera - User manual

settings.

Open: Click to open AXIS Image Health Analytics. The application opens up in a new browser tab where you can configure its settings.

Not installed: AXIS Image Health Analytics is not installed on this device. Upgrade AXIS OS to the latest version to get the latest version of the application.

Metadata visualization

The camera detects moving objects and classes them according to object type. In the view, a classified object has a colored bounding box around it along with its assigned id.

Id: A unique identification number for the identified object and the type. This number is shown in both the list and the view.

Type: Classifies a moving object as Human, Face, Car, Bus, Truck, Bike, or License Plate. The color of the bounding box depends on the type classification.

Confidence: The bar indicates the level of confidence in the classification of the



AXIS Q6088-E PTZ Camera - User manual

RTSP metadata producers

View and manage the data channels that stream metadata and the channels they use.

Note

These settings are for the RTSP metadata stream that uses ONVIF XML. Changes made here don't affect the Metadata visualization page.

Producer: A data channel that uses Real-Time Streaming Protocol (RTSP) to send metadata.

Channel: The channel used to send metadata from a producer. Turn on to enable the metadata stream. Turn off for compatibility or resource management reasons.

MQTT

Configure the producers that generate and stream metadata over MQTT (Message Queuing Telemetry Transport).

Create: Click to create a new MQTT producer.



AXIS Q6088-E PTZ Camera - User manual

MQTT topic: Enter a name for the MQTT topic.

QoS (Quality of Service): Set the level of message delivery assurance (0-2).

Retain messages: Choose whether to retain the last message on the MQTT topic.

Use MQTT client device topic prefix: Choose whether to add a prefix to the MQTT topic to help identify the source device.

The context menu contains:

Update: Modify the settings of the selected producer.

Delete: Delete the selected producer.

Object snapshot: Turn on to include a cropped image of each detected object.

Additional crop margin: Turn on to add extra margin around cropped images of detected objects.

PTZ



AXIS Q6088-E PTZ Camera - User manual

quickly navigate between different fields of view. If your device supports guard tours, you can use preset positions to create automated guard tours.

Preset positions

Create preset position: Create a new preset position based on the current position of your camera.

Thumbnail: Turn on to add a thumbnail image for the preset position.

Name: Enter a name for the preset position.

Home position: Turn on to set this position as your camera's default field of view. The home position is marked with

. Your camera will always have a home position.

Settings

Return to home position when inactive: Turn on to make the



AXIS Q6088-E PTZ Camera - User manual

new preset position you create.

The context menu contains:

Create thumbnails

: Create a thumbnail for all your preset positions.

Refresh thumbnails: Replace the thumbnails for your preset positions with new and updated thumbnails.

Delete all preset positions: Remove all your preset positions. This will also create a new home position automatically.

Guard tours

Guard tour: Create a guard tour.



AXIS Q6088-E PTZ Camera - User manual

Preset position

A guard tour with preset positions continuously streams footage from a selection of preset positions in a random or fixed sequence. You can choose how long the camera should stay at each preset position before moving on to the next. The guard tour will continue to run in an endless loop until you stop it, even when there are no clients (web browsers) streaming the footage.

Settings

General settings

Name: Enter a name for the guard tour.

Play guard tour in random order: Turn on to make the camera move unpredictably between the preset positions during the guard tour.

Pause between runs: Enter your desired time interval between guard tours. You can enter any interval from 0 minutes to 2 hours and 45 minutes.

Step settings

Duration: Choose how long you want the camera to stay at each preset position. The default value is 10 seconds, and the maximum allowed value is 60 minutes.

Move speed: Choose how quickly you want the camera to move to



AXIS Q6088-E PTZ Camera - User manual

positions, press SHIFT while selecting the preset positions. Click

and drag the preset positions to the **View order** area.

View order: Displays the preset positions included in the guard tour.

Import all preset positions: Add all preset positions in the order they were created, starting from the oldest one.

: Start the guard tour.

Recorded

A recorded tour replays a sequence of recorded pan/tilt/zoom movements, including their variable speeds and lengths.

General settings

Name: Enter a name for the guard tour.

Pause between runs: Enter your desired time interval between guard



AXIS Q6088-E PTZ Camera - User manual

Start recording tour: Start recording the pan/tilt/zoom movements you want the guard tour to replicate.

Stop recording tour: Stop recording the pan/tilt/zoom movements you want the guard tour to replicate.

Re-record: Start a new recording of pan/tilt/zoom movements. This will overwrite your most recent recording.

Start the recorded tour.

Pause the recorded tour.

Stop the recorded tour.

Limits



AXIS Q6088-E PTZ Camera - User manual

Save as Home: Click to set the current position as zero-point for pan coordinates.

Pan-tilt limits: The camera uses the coordinates of the center of the image when you set pan-tilt limits.

Left pan limit: Click to limit the camera's pan movements to the left. Click again to remove the limit.

Right pan limit: Click to limit the camera's pan movements to the right. Click again to remove the limit.

Top tilt limit: Click to limit the camera's tilt movements to the top. Click again to remove the limit.



AXIS Q6088-E PTZ Camera - User manual

Bottom tilt limit: Click to limit the camera's tilt movements to the bottom. Click again to remove the limit.

Auto-flip

:

Enables the camera head to instantly reverse 360° and continue to pan beyond its mechanical limit.

E-flip

:

Automatically corrects the camera view by flipping the image 180° when the camera tilts beyond -90°.

Nadir-flip

:

Enables the camera to pan 180° when tilting beyond -90°, and then continue upwards.



AXIS Q6088-E PTZ Camera - User manual

Near focus limit: Select a value to prevent the camera from autofocusing on objects close to the camera. This way, the camera can ignore objects such as overhead wires, streetlights, or other nearby objects. To make the camera focus on the areas of interest, set the near focus limit to a value greater than the distance at which the objects of no interest tend to appear.

Motion

Proportional speed

:

Turn on to set the maximum proportional speed.

Max proportional speed

: Set a value between 1 and 1000 to limit the pan and tilt speed. Max proportional speed is defined as a percentage, where the value 1000 equals 1000%.



AXIS Q6088-E PTZ Camera - User manual

and the max proportional speed is set to 100 (100%), the maximum speed is about 44 degrees/second. If the image is then zoomed in from 44 to 10 degrees wide, the maximum speed reaches about 10 degrees/second, which is probably too fast for easy viewing. To limit the speed, set the max proportional speed to 50 (50%). This way, the maximum speed only reaches 50% of the maximum for the currently selected zoom level. This means that when the image is 44 degrees wide, the greatest possible speed is limited to about 22 degrees/second, and when the view is zoomed in to 10 degrees the speed is limited to about 5 degrees/second.

Adjustable zoom speed: Turn on to use variable speeds when controlling the zoom with a joystick or a mouse wheel. The zoom speed is automatically set through the command `continuouszoommove` in the VAPIX® Application Programming Interface (API). Turn off to use the highest zoom speed which is the same speed for moving to presets.

Freeze image on PTZ

Off: Never freeze image.

All movements: Freeze the image while the camera is moving. Once the camera reaches its new position, the view from that position is shown.

Preset positions: Freeze the image only when the camera moves



AXIS Q6088-E PTZ Camera - User manual

OSDI zones

On-screen direction indicator (OSDI) gives information of the direction the camera is pointing at in the text overlay. The camera uses the coordinates of the center of the image when you set the lower left and upper right zone area.

Create OSDI zone: Click to create an OSDI zone.

Name: Enter a name for the zone.

Active: Turn on to display the zone in the live view.

Zone limits

: Navigate to your desired position, and click the icon to set the lower left point of the zone. Click again to unset the lower left point.



AXIS Q6088-E PTZ Camera - User manual

: Navigate to your desired position, and click the icon to set the upper right point of the zone. Click again to unset the upper right point.

Go to: Click to go to the lower left point or the upper right point of the zone.

The context menu contains:

Create multiple zones: Click to create multiple zones. Enter a name for the zone, and specify the coordinates for lower left and upper right of the zone.

Add zone coordinates: Click to specify the parameters for another zone.

Delete all zones: Click to delete all zones.

Orientation aid

Orientation aid: Turn on to activate overlays of user-defined points of interest at the correct bearing and a 2D-compass synchronized to the cameras movements, including a field of view.



AXIS Q6088-E PTZ Camera - User manual

Preset positions: Select the preset positions used for orientation aid.

To select an individual preset position, click the preset position.

To select all preset positions, click

.

Gatekeeper

A gatekeeper monitors an area such as an entrance gate. When motion is detected in the monitored area, the gatekeeper steers the camera to a selected preset position. Using a zoomed-in preset position can make it possible to, for example, read a license plate or identify a person. When motion is no longer detected, the camera returns to its home position after a defined time.

Control queue

User control queue

PTZ control queue: Turn on to place PTZ control requests in a queue. This displays the users status and position in the queue. To use the PTZ controls in AXIS Camera Station, turn off this setting.



AXIS Q6088-E PTZ Camera - User manual

the PTZ control.

The user groups are listed in a prioritized order with the highest priority on top. To change the priority of a user group, click

and drag the user group up or down. For each user group:

Timeout duration: Set the amount of time to wait before timeout. The default value is 1 minute, and allowed values are from 1 second to 60 minutes.

Timeout type

Timespan: Time out after reaching the set duration.

Activity: Time out after reaching the set duration since the last activity.

Infinity: Never to time out until a user with higher priority takes control.

Use cookie: Select to allow the camera to recognize and separate users within the same user group.

Settings



AXIS Q6088-E PTZ Camera - User manual

Control queue poll time: Set how often to poll the camera to update the place of the users or user groups in the queue. The default value is 20 seconds, and allowed values are from 5 seconds to 60 minutes.

Recordings

Ongoing recordings: Show all ongoing recordings on the device.

Start a recording on the device.

Choose which storage device to save to.

Stop a recording on the device.



AXIS Q6088-E PTZ Camera - User manual

manually stopped. Even if the device is shut down, the recording will continue when the device starts up again.

Play the recording.

Stop playing the recording.

Show or hide information and options about the recording.

Set export range: If you only want to export part of the recording, enter a time



AXIS Q6088-E PTZ Camera - User manual

Encrypt: Select to set a password for exported recordings. It will not be possible to open the exported file without the password.

Click to delete a recording.

Export: Export the whole or a part of the recording.

Click to filter the recordings.

From: Show recordings done after a certain point in time.

To: Show recordings up until a certain point in time.

Source

:



AXIS Q6088-E PTZ Camera - User manual

Storage: Show recordings based on storage type.

Apps

Add app: Install a new app.

Find more apps: Find more apps to install. You will be taken to an overview page of Axis apps.

Allow unsigned apps

:

Turn on to allow installation of unsigned apps.

View the security updates in AXIS OS and ACAP apps.

Note



AXIS Q6088-E PTZ Camera - User manual

Use the switch next to the app name to start or stop the app.

Open: Access the app's settings. The available settings depend on the application. Some applications don't have any settings.

The context menu can contain one or more of the following options:

Open-source license: View information about open-source licenses used in the app.

App log: View a log of the app events. The log is helpful when you contact support.

Activate license with a key: If the app requires a license, you need to activate it. Use this option if your device doesn't have internet access. If you don't have a license key, go to axis.com/products/analytics. You need a license code and the Axis product serial number to generate a license key.

Activate license automatically: If the app requires a license, you need to activate it. Use this option if your



AXIS Q6088-E PTZ Camera - User manual

license, for example, when you change from a trial license to a full license. If you deactivate the license, you also remove it from the device.

Settings: Configure the parameters.

Delete: Delete the app permanently from the device. If you don't deactivate the license first, it remains active.

System

Time and location

Date and time

The time format depends on the web browser's language settings.

Note

We recommend you synchronize the device's date and time with an NTP server.

Synchronization: Select an option for the device's date and time synchronization.

Automatic date and time (PTP): Synchronize using the precision time protocol.

Automatic date and time (manual NTS KE servers): Synchronize with the secure NTP key establishment



AXIS Q6088-E PTZ Camera - User manual

servers. When you use two NTP servers, the device synchronizes and adapts its time based on input from both.

Trusted NTS KE CA certificates:

Select the trusted CA certificates to use for secure NTS KE time synchronization, or leave at none.

Max NTP poll time: Select the maximum amount of time the device should wait before it polls the NTP server to get an updated time.

Min NTP poll time: Select the minimum amount of time the device should wait before it polls the NTP server to get an updated time.

Automatic date and time (NTP servers using DHCP): Synchronize with the NTP servers connected to the DHCP server.

Fallback NTP servers: Enter the IP address of one or two fallback servers.

Max NTP poll time: Select the maximum amount of time the device should wait before it polls the NTP server to get an updated time.

Min NTP poll time: Select the minimum amount of time the device should wait before it polls the NTP server to get an updated time.



AXIS Q6088-E PTZ Camera - User manual

address of one or two NTP servers. When you use two NTP servers, the device synchronizes and adapts its time based on input from both.

Max NTP poll time: Select the maximum amount of time the device should wait before it polls the NTP server to get an updated time.

Min NTP poll time: Select the minimum amount of time the device should wait before it polls the NTP server to get an updated time.

Custom date and time: Manually set the date and time. Click **Get from system** to fetch the date and time settings once from your computer or mobile device.

Time zone: Select which time zone to use. Time will automatically adjust to daylight saving time and standard time.

DHCP: Adopts the time zone of the DHCP server. The device must be connected to a DHCP server before you can select this option.

Manual: Select a time zone from the drop-down list.

Note

The system uses the date and time settings in all recordings, logs, and system settings.



AXIS Q6088-E PTZ Camera - User manual

management system can use this information to place the device on a map.

Latitude: Positive values are north of the equator.

Longitude: Positive values are east of the prime meridian.

Heading: Enter the compass direction that the device is facing. 0 is due north.

Label: Enter a descriptive name for your device.

Save: Click to save your device location.

Regional settings

Sets the system of measurement to use in all system settings.

Metric (m, km/h): Select for distance measurement to be in meters and speed measurement to be in kilometers per hour.

U.S. customary (ft, mph): Select for distance measurement to be in feet and speed measurement to be in miles per hour.

Network

IPv4



AXIS Q6088-E PTZ Camera - User manual

configuration. We recommend using automatic IP assignment (DHCP) for most networks.

IP address: Enter a unique IP address for the device. Static IP addresses can be assigned at random within isolated networks, provided that each address is unique. To avoid conflicts, we recommend you contact your network administrator before you assign a static IP address.

Subnet mask: Enter the subnet mask to define what addresses are inside the local area network. Any address outside the local area network goes through the router.

Router: Enter the IP address of the default router (gateway) used to connect devices that are attached to different networks and network segments.

Fallback to static IP address if DHCP isn't available: Select if you want to add a static IP address to use as fallback if DHCP is unavailable and can't assign an IP address automatically.

Note

If DHCP isn't available and the device uses a static address fallback, the static address is configured with a limited scope.

IPv6



AXIS Q6088-E PTZ Camera - User manual

Hostname

Assign hostname automatically: Select to let the network router assign a hostname to the device automatically.

Hostname: Enter the hostname manually to use as an alternative way of accessing the device. The server report and system log use the hostname. Allowed characters are A-Z, a-z, 0-9 and -.

Enable dynamic DNS updates: Allow your device to automatically update its domain name server records whenever its IP address changes.

Register DNS name: Enter a unique domain name that points to your device's IP address. Allowed characters are A-Z, a-z, 0-9 and -.

TTL: Time to Live (TTL) sets how long a DNS record stays valid before it needs to be updated.

DNS servers

Assign DNS automatically: Select to let the DHCP server assign search domains and DNS server addresses to the device automatically. We recommend automatic DNS (DHCP) for most networks.

Search domains: When you use a hostname that is not fully qualified, click **Add search domain** and enter a domain



AXIS Q6088-E PTZ Camera - User manual

This provides the translation of hostnames to IP addresses on your network.

Note

If DHCP is disabled, features that rely on automatic network configuration, such as hostname, DNS servers, NTP, and others, may stop working.

HTTP and HTTPS

HTTPS is a protocol that provides encryption for page requests from users and for the pages returned by the web server. The encrypted exchange of information is governed by the use of an HTTPS certificate, which guarantees the authenticity of the server.

To use HTTPS on the device, you must install an HTTPS certificate. Go to **System > Security** to create and install certificates.

Allow access through: Select if a user is allowed to connect to the device through the **HTTP**, **HTTPS**, or both **HTTP and HTTPS** protocols.

Note

If you view encrypted web pages through HTTPS, you might experience a drop in performance, especially when you request a page for the first time.



AXIS Q6088-E PTZ Camera - User manual

any port in the range 1-1023. If you use a port in this range, you get a warning.

HTTPS port: Enter the HTTPS port to use. The device allows port 443 or any port in the range 1024-65535. If you are logged in as an administrator, you can also enter any port in the range 1-1023. If you use a port in this range, you get a warning.

Certificate: Select a certificate to enable HTTPS for the device.

Network discovery protocols



AXIS Q6088-E PTZ Camera - User manual

be visible on the network. The default name is the device name and MAC address.

UPnP®: Turn on to allow automatic discovery on the network.

UPnP name: Enter a friendly name to be visible on the network. The default name is the device name and MAC address.

WS-Discovery: Turn on to allow automatic discovery on the network.

LLDP and CDP: Turn on to allow automatic discovery on the network. Turning LLDP and CDP off can impact the PoE power negotiation. To resolve any issues with the PoE power negotiation, configure the PoE switch for hardware PoE power negotiation only.

Global proxies

Http proxy: Specify a global proxy host or IP address according to the allowed format.

Https proxy: Specify a global proxy host or IP address according to the allowed format.

Allowed formats for http and https proxies:

"http(s)://host:port"

"http(s)://user@host:port"

"http(s)://user:pass@host:port"



AXIS Q6088-E PTZ Camera - User manual

No proxy: Use **No proxy** to bypass global proxies. Enter one of the options in the list, or enter several separated by a comma:

Leave empty

Specify an IP address

Specify an IP address in CIDR format

Specify a domain name, for example:
"www.<domain name>.com"

Specify all subdomains in a specific domain, for example ".<domain name>.com"

One-click cloud connection

One-click cloud connection (O3C) together with an O3C service provides easy and secure internet access to live and recorded video from any location. For more information, see axis.com/end-to-end-solutions/hosted-services.

Allow O3C:

One-click: This is the default option. To connect to O3C, press the control button on the device. Depending on the device model, either press and release or press and hold, until the status LED flashes. Register the device with the O3C service within 24 hours to enable **Always** and stay connected. If you don't register, the device will disconnect from O3C.



AXIS Q6088-E PTZ Camera - User manual

connected. Use this option if the control button is out of reach.

No: Disconnects the O3C service.

Proxy settings: If needed, enter the proxy settings to connect to the proxy server.

Host: Enter the proxy server's address.

Port: Enter the port number used for access.

Login and Password: If needed, enter username and password for the proxy server.

Authentication method:

Basic: This method is the most compatible authentication scheme for HTTP. It's less secure than the **Digest** method because it sends the username and password unencrypted to the server.

Digest: This method is more secure because it always transfers the password encrypted across the network.

Auto: This option lets the device select the authentication method depending on the supported methods. It prioritizes the **Digest** method over the **Basic** method.

Owner authentication key (OAK): Click **Get key** to fetch the owner authentication key. This is only possible if the device is connected to the internet without a firewall or proxy.



AXIS Q6088-E PTZ Camera - User manual

SNMP: Select the version of SNMP to use.

v1 and v2c:

Read community: Enter the community name that has read-only access to all supported SNMP objects. The default value is **public**.

Write community: Enter the community name that has read or write access to all supported SNMP objects (except read-only objects). The default value is **write**.

Activate traps: Turn on to activate trap reporting. The device uses traps to send messages for important events or status changes to a management system. In the web interface, you can set up traps for SNMP v1 and v2c. Traps are automatically turned off if you change to SNMP v3 or turn off SNMP. If you use SNMP v3, you can set up traps through the SNMP v3 management application.

Trap address: Enter the IP address or host name of the management server.

Trap community: Enter the community to use when the device sends a trap message to the management system.

Traps:



AXIS Q6088-E PTZ Camera - User manual

when a link changes from down to up.

Link down: Sends a trap message when a link changes from up to down.

Authentication failed: Sends a trap message when an authentication attempt fails.

Note

All Axis Video MIB traps are enabled when you turn on SNMP v1 and v2c traps. For more information, see [AXIS OS Portal > SNMP](#).

v3: SNMP v3 is a more secure version, which provides encryption and secure passwords. To use SNMP v3, we recommend you to activate HTTPS, as the password is then sent through HTTPS. This also prevents unauthorized parties' access to unencrypted SNMP v1 and v2c traps. If you use SNMP v3, you can set up traps through the SNMP v3 management application.

Privacy: Select what encryption to use for protecting your SNMP data.

Password for the account

"initial": Enter the SNMP password for the account named "initial". Although the password can be sent without activating HTTPS, we don't recommend it. The SNMP v3 password can only



AXIS Q6088-E PTZ Camera - User manual

reset the device to factory default settings.

Security

Certificates

Certificates are used to authenticate devices on a network. The device supports two types of certificates:

Client/server certificates

A client/server certificate validates the device's identity, and can be self-signed or issued by a Certificate Authority (CA). A self-signed certificate offers limited protection and can be used before a CA-issued certificate has been obtained.

CA certificates

You can use a CA certificate to authenticate a peer certificate, for example to validate the identity of an authentication server when the device connects to a network protected by IEEE 802.1X. The device has several pre-installed CA certificates.

These formats are supported:

Certificate formats: .PEM, .CER, and .PFX

Private key formats: PKCS#1 and PKCS#12



AXIS Q6088-E PTZ Camera - User manual

reinstalled.

Add certificate : Click to add a certificate. A step-by-step guide opens up.

More

: Show more fields to fill in or select.

Secure keystore: Select to use **Trusted Execution Environment (SoC TEE)**, **Secure element** or **Trusted Platform Module 2.0** to securely store the private key. For more information on which secure keystore to select, go to [help.axis.com/axis-os#cryptographic-support](https://help.axis.com/en-us/axis-os#cryptographic-support).

Key type: Select the default or a different encryption algorithm from the drop-down list to protect the certificate.



AXIS Q6088-E PTZ Camera - User manual

The context menu contains:

Certificate information: View an installed certificate's properties.

Delete certificate: Delete the certificate.

Create certificate signing request: Create a certificate signing request to send to a registration authority to apply for a digital identity certificate.

Secure keystore

:

Trusted Execution Environment (SoC TEE): Select to use SoC TEE for secure keystore.

Secure element (CC EAL6+, FIPS 140-3 Level 3)

: Select to use secure element for secure keystore.

Trusted Platform Module 2.0 (CC EAL4+, FIPS 140-2 Level 2)



AXIS Q6088-E PTZ Camera - User manual

: Select to use TPM 2.0 for secure keystore.

Cryptographic policy

The cryptographic policy defines how encryption is used to protect data.

Active: Select which cryptographic policy to apply to the device:

Default — OpenSSL: Balanced security and performance for general use.

FIPS — Policy to comply with FIPS 140-2: Encryption compliant with FIPS 140-2 for regulated industries.

Network access control and encryption

IEEE 802.1x

IEEE 802.1x is an IEEE standard for port-based network admission control providing secure authentication of wired and wireless network devices. IEEE 802.1x is based on EAP (Extensible Authentication Protocol).

To access a network protected by IEEE 802.1x, network devices must authenticate themselves. The authentication is performed by an authentication server, typically a RADIUS server (for example, FreeRADIUS and Microsoft Internet Authentication Server).



AXIS Q6088-E PTZ Camera - User manual

confidentiality and integrity for media access independent protocols.

Certificates

When configured without a CA certificate, server certificate validation is disabled and the device tries to authenticate itself regardless of what network it is connected to.

When using a certificate, in Axis' implementation, the device and the authentication server authenticate themselves with digital certificates using EAP-TLS (Extensible Authentication Protocol - Transport Layer Security).

To allow the device to access a network protected through certificates, you must install a signed client certificate on the device.

Authentication method: Select an EAP type used for authentication.

Client certificate: Select a client certificate to use IEEE 802.1x. The authentication server uses the certificate to validate the client's identity.

CA certificates: Select CA certificates to validate the authentication server's identity. When no certificate is selected, the device tries to authenticate itself regardless of what network it is connected to.

EAP identity: Enter the user identity associated with the client certificate.



AXIS Q6088-E PTZ Camera - User manual

These settings are only available if you use **IEEE 802.1x PEAP-MSCHAPv2** as the authentication method:

Password: Enter the password for your user identity.

Peap version: Select the Peap version that is used in the network switch.

Label: Select 1 to use client EAP encryption; select 2 to use client PEAP encryption. Select the Label that the network switch uses when using Peap version 1.

These settings are only available if you use **IEEE 802.1ae MACsec (Static CAK/Pre-Shared Key)** as the authentication method:

Key agreement connectivity association key name: Enter the connectivity association name (CKN). It must be 2 to 64 (divisible by 2) hexadecimal characters. The CKN must be manually configured in the connectivity association and must match on both ends of the link to initially enable MACsec.

Key agreement connectivity association key: Enter the connectivity association key (CAK). It should be either 32 or 64 hexadecimal characters long. The CAK must be manually configured in the connectivity association and



AXIS Q6088-E PTZ Camera - User manual

Blocking: Turn on to block brute-force attacks. A brute-force attack uses trial-and-error to guess login info or encryption keys.

Blocking period: Enter the number of seconds to block a brute-force attack.

Blocking conditions: Enter the number of authentication failures allowed per second before the block starts. You can set the number of failures allowed both on page level and device level.

Firewall

Firewall: Turn on to activate the firewall.

Default Policy: Select how you want the firewall to handle connection requests not covered by rules.

ACCEPT: Allows all connections to the device. This option is set by default.

DROP: Blocks all connections to the device.

To make exceptions to the default policy, you can create rules that allows or blocks connections to the device from specific addresses, protocols, and ports.

+ **New rule:** Click to create a rule.

Rule type:



AXIS Q6088-E PTZ Camera - User manual

the firewall rule.

IP range: Select to specify a range of addresses to allow or block. Use IPv4/IPv6 in **Start** and **End**.

IP address: Enter an address that you want to allow or block. Use IPv4/IPv6 or CIDR format.

Protocol: Select a network protocol (TCP, UDP, or Both) to allow or block. If you select a protocol, you must also specify a port.

MAC: Enter the MAC address of a device that you want to allow or block.

Port range: Select to specify the range of ports to allow or block. Add them in **Start** and **End**.

Port: Enter a port number that you want to allow or block. Port numbers must be between 1 and 65535.

Traffic type: Select a traffic type that you want to allow or block.

UNICAST: Traffic from a single sender to a single recipient.

BROADCAST: Traffic from a single sender to all devices on the network.

MULTICAST: Traffic from one or more senders to one or more recipient.

LIMIT: Select to accept connections from devices that match the criteria



AXIS Q6088-E PTZ Camera - User manual

Use IPv4/IPv6 in **Start** and **End**.

IP address: Enter an address that you want to allow or block. Use IPv4/IPv6 or CIDR format.

Protocol: Select a network protocol (TCP, UDP, or Both) to allow or block. If you select a protocol, you must also specify a port.

MAC: Enter the MAC address of a device that you want to allow or block.

Port range: Select to specify the range of ports to allow or block. Add them in **Start** and **End**.

Port: Enter a port number that you want to allow or block. Port numbers must be between 1 and 65535.

Unit: Select the type of connections to allow or block.

Period: Select the time period related to **Amount**.

Amount: Set the maximum number of times a device is allowed to connect within the set **Period**. The maximum amount is 65535.

Burst: Enter the number of connections allowed to exceed the set **Amount** once during the set **Period**. Once the number has been reached, only the set amount during the set period is allowed.



AXIS Q6088-E PTZ Camera - User manual

BROADCAST: Traffic from a single sender to all devices on the network.

MULTICAST: Traffic from one or more senders to one or more recipient.

Test rules: Click to test the rules that you have defined.

Test time in seconds: Set a time limit for testing the rules.

Roll back: Click to roll back the firewall to its previous state, before you have tested the rules.

Apply rules: Click to activate the rules without testing. We don't recommend that you do this.

Custom signed AXIS OS certificate

To install test software or other custom software from Axis on the device, you need a custom signed AXIS OS certificate. The certificate verifies that the software is approved by both the device owner and Axis. The software can only run on a specific device which is identified by its unique serial number and chip ID. Only Axis can create custom signed AXIS OS certificates, since Axis holds the key to sign them.

Install: Click to install the certificate. You need to install the certificate before you install the software.



AXIS Q6088-E PTZ Camera - User manual

The context menu contains:

Delete certificate: Delete the certificate.

Accounts

Accounts

Add account: Click to add a new account. You can add up to 100 accounts.

Account: Enter a unique account name.

New password: Enter a password for the account. Passwords must be 1 to 64 characters long. Only ASCII printable characters (code 32 to 126) are allowed in the password, for example, letters, numbers, punctuation, and some symbols.

Repeat password: Enter the same password again.

Privileges:

Administrator: Has full access to all settings. Administrators can also add, update, and remove other accounts.



AXIS Q6088-E PTZ Camera - User manual

Watch and take snapshots of a video stream.

Watch and export recordings.

Pan, tilt, and zoom; with **PTZ account** access.

The context menu contains:

Update account: Edit the account properties.

Delete account: Delete the account. You can't delete the root account.

Anonymous access

Allow anonymous viewing: Turn on to allow anyone access the device as a viewer without logging in with an account.

Allow anonymous PTZ operating

:

Turn on to allow anonymous users to pan, tilt, and zoom the image.



AXIS Q6088-E PTZ Camera - User manual

Add SSH account: Click to add a new SSH account.

Enable SSH: Turn on to use SSH service.

Account: Enter a unique account name.

New password: Enter a password for the account. Passwords must be 1 to 64 characters long. Only ASCII printable characters (code 32 to 126) are allowed in the password, for example, letters, numbers, punctuation, and some symbols.

Repeat password: Enter the same password again.

Comment: Enter a comment (optional).

The context menu contains:

Update SSH account: Edit the account properties.

Delete SSH account: Delete the account. You can't delete the root account.

Virtual host



AXIS Q6088-E PTZ Camera - User manual

Add virtual host: Click to add a new virtual host.

Enabled: Select to use this virtual host.

Server name: Enter the name of the server. Only use numbers 0-9, letters A-Z, and hyphen (-).

Port: Enter the port the server is connected to.

Type: Select the type of authentication to use. Select between **Basic**, **Digest**, and **Open ID**.

The context menu contains:

Update: Update the virtual host.

Delete: Delete the virtual host.

Disabled: The server is disabled.

Client Credentials Grant Configuration

Admin claim: Enter a value for the admin role.

Verification URI: Enter the web link for the API endpoint authentication.



AXIS Q6088-E PTZ Camera - User manual

Viewer claim: Enter the value for the viewer role.

Save: Click to save the values.

OpenID Configuration

Important

If you can't use OpenID to sign in, use the Digest or Basic credentials you used when you configured OpenID to sign in.

Client ID: Enter the OpenID username.

Outgoing Proxy: Enter the proxy address for the OpenID connection to use a proxy server.

Admin claim: Enter a value for the admin role.

Provider URL: Enter the web link for the API endpoint authentication. Format should be https://[insert URL]/.well-known/openid-configuration

Operator claim: Enter a value for the operator role.

Require claim: Enter the data that should be in the token.

Viewer claim: Enter the value for the viewer role.

Remote user: Enter a value to identify remote users. This assists to display the current user in the device's web interface.



AXIS Q6088-E PTZ Camera - User manual

Save: Click to save the OpenID values.

Enable OpenID: Turn on to close current connection and allow device authentication from the provider URL.

Events

Rules

A rule defines the conditions that triggers the product to perform an action. The list shows all the currently configured rules in the product.

Note

You can create up to 256 action rules.

Add a rule: Create a rule.

Name: Enter a name for the rule.

Wait between actions: Enter the minimum time (hh:mm:ss) that must pass between rule activations. It is useful if the rule is activated by, for example, day-night mode conditions, to avoid that small light changes during sunrise and sunset activate the rule repeatedly.



AXIS Q6088-E PTZ Camera - User manual

specific conditions, see [Get started with rules for events](#).

Use this condition as a trigger: Select to make this first condition function only as a starting trigger. It means that once the rule is activated, it remains active for as long as all the other conditions are met, no matter the state of the first condition. If you don't select this option, the rule will simply be active whenever all the conditions are met.

Invert this condition: Select if you want the condition to be the opposite of your selection.

Add a condition: Click to add an additional condition.

Action: Select an action from the list and enter its required information. For information about specific actions, see [Get started with rules for events](#).

Recipients

You can set up your device to notify recipients about events or send files.

Note



AXIS Q6088-E PTZ Camera - User manual

one image per event can be sent.

The list shows all the recipients currently configured in the product, along with information about their configuration.

Note

You can create up to 20 recipients.

Add a recipient: Click to add a recipient.

Name: Enter a name for the recipient.

Type: Select from the list:

FTP

Host: Enter the server's IP address or hostname. If you enter a hostname, make sure that a DNS server is specified under **System > Network > IPv4 and IPv6**.

Port: Enter the port number used by the FTP server. The default is



AXIS Q6088-E PTZ Camera - User manual

already exist on the FTP server, you will get an error message when uploading files.

Username: Enter the username for the login.

Password: Enter the password for the login.

Use temporary file name: Select to upload files with temporary, automatically generated filenames. The files get renamed to the desired names when the upload completes. If the upload is aborted/interrupted, you don't get any corrupt files. However, you probably still get the temporary files. This way you know that all files that have the desired name are correct.

Use passive FTP: Under normal circumstances, the product simply requests the target FTP server to open the data connection. The device actively initiates both the FTP control and data connections to the target server. This is normally needed if there is a firewall between the device and the target FTP server.

HTTP

URL: Enter the network address to the HTTP server and the script that will handle the request. For example,
`http://192.168.254.10/cgi-bin/notify.cgi.`



AXIS Q6088-E PTZ Camera - User manual

Proxy: Turn on and enter the required information if a proxy server must be passed to connect to the HTTP server.

HTTPS

URL: Enter the network address to the HTTPS server and the script that will handle the request. For example, `https://192.168.254.10/cgi-bin/notify.cgi`.

Validate server certificate: Select to validate the certificate that was created by HTTPS server.

Username: Enter the username for the login.

Password: Enter the password for the login.

Proxy: Turn on and enter the required information if a proxy server must be passed to connect to the HTTPS server.

Network storage

You can add network storage such as NAS (network-attached storage) and use it as a recipient to store files. The files are stored in the Matroska (MKV) file format.



AXIS Q6088-E PTZ Camera - User manual

share on the host.

Folder: Enter the path to the directory where you want to store files.

Username: Enter the username for the login.

Password: Enter the password for the login.

SFTP

Host: Enter the server's IP address or hostname. If you enter a hostname, make sure that a DNS server is specified under **System > Network > IPv4 and IPv6**.

Port: Enter the port number used by the SFTP server. The default is 22.

Folder: Enter the path to the directory where you want to store files. If this directory doesn't already exist on the SFTP server, you will get an error message when uploading files.

Username: Enter the username for the login.

Password: Enter the password for the login.



AXIS Q6088-E PTZ Camera - User manual

SFTP client supports SFTP servers using SSH-2 with RSA, DSA, ECDSA, and ED25519 host key types. RSA is the preferred method during negotiation, followed by ECDSA, ED25519, and DSA. Make sure to enter the right MD5 host key that is used by your SFTP server. While the Axis device supports both MD5 and SHA-256 hash keys, we recommend using SHA-256 due to stronger security over MD5. For more information on how to configure an SFTP server with an Axis device, go to the [AXIS OS Portal](#).

SSH host public key type

(SHA256): Enter the fingerprint of the remote host's public key (a 43-digit Base64 encoded string). The SFTP client supports SFTP servers using SSH-2 with RSA, DSA, ECDSA, and ED25519 host key types. RSA is the preferred method during negotiation, followed by ECDSA, ED25519, and DSA. Make sure to enter the right MD5 host key that is used by your SFTP server. While the Axis device supports both MD5 and SHA-256 hash keys, we recommend using SHA-256 due to stronger security over MD5. For more information on how to configure an SFTP server with an Axis device, go to the [AXIS OS Portal](#).

Use temporary file name: Select to upload files with temporary,



AXIS Q6088-E PTZ Camera - User manual

get any corrupt files. However, you probably still get the temporary files. This way, you know that all files that have the desired name are correct.

SIP or VMS

:

SIP: Select to make a SIP call.

VMS: Select to make a VMS call.

From SIP account: Select from the list.

To SIP address: Enter the SIP address.

Test: Click to test that your call settings works.

Email

Send email to: Enter the email address to send emails to. To enter multiple addresses, use commas to separate them.

Send email from: Enter the email address of the sending server.

Username: Enter the username for the mail server. Leave this field empty if the mail server does not require authentication.



AXIS Q6088-E PTZ Camera - User manual

Email server (SMTP): Enter the name of the SMTP server, for example, smtp.gmail.com, smtp.mail.yahoo.com.

Port: Enter the port number for the SMTP server, using values in the range 0-65535. The default value is 587.

Encryption: To use encryption, select either SSL or TLS.

Validate server certificate: If you use encryption, select to validate the identity of the device. The certificate can be self-signed or issued by a Certificate Authority (CA).

POP authentication: Turn on to enter the name of the POP server, for example, pop.gmail.com.

Note

Some email providers have security filters that prevent users from receiving or viewing large amount of attachments, from receiving scheduled emails and similar. Check the email provider's security policy to avoid your email account being locked or missing out on your expected emails.

TCP



AXIS Q6088-E PTZ Camera - User manual

System > Network > IPv4 and IPv6.

Port: Enter the port number used to access the server.

Test: Click to test the setup.

The context menu contains:

View recipient: Click to view all the recipient details.

Copy recipient: Click to copy a recipient. When you copy, you can make changes to the new recipient.

Delete recipient: Click to delete the recipient permanently.

Schedules

Schedules and pulses can be used as conditions in rules. The list shows all the schedules and pulses currently configured in the product, along with information about their configuration.



AXIS Q6088-E PTZ Camera - User manual

Add schedule: Click to create a schedule or pulse.

Manual triggers

You can use the manual trigger to manually trigger a rule. The manual trigger can, for example, be used to validate actions during product installation and configuration.

MQTT



AXIS Q6088-E PTZ Camera - User manual

and is used in a wide variety of industries to connect remote devices with a small code footprint and minimal network bandwidth. The MQTT client in Axis device software can simplify integration of data and events produced in the device to systems which are not video management software (VMS).

Set up the device as an MQTT client. MQTT communication is based on two entities, the clients and the broker. The clients can send and receive messages. The broker is responsible for routing messages between clients.

You can learn more about MQTT in [AXIS OS Knowledge base](#).

ALPN

ALPN is a TLS/SSL extension that allows for the selection of an application protocol during the handshake phase of the connection between the client and server. This is used to enable MQTT traffic over the same port that is used for other protocols, such as HTTP. In some cases, there might not be a dedicated port open for MQTT communication. A solution in such cases is to use ALPN to negotiate the use of MQTT as the application protocol



AXIS Q6088-E PTZ Camera - User manual

MQTT client

Connect: Turn on or off the MQTT client.

Status: Shows the current status of the MQTT client.

Broker

Host: Enter the hostname or IP address of the MQTT server.

Protocol: Select which protocol to use.

Port: Enter the port number.

1883 is the default value for **MQTT over TCP**

8883 is the default value for **MQTT over SSL**

80 is the default value for **MQTT over WebSocket**

443 is the default value for **MQTT over WebSocket Secure**

ALPN protocol: Enter the ALPN protocol name provided by your MQTT broker provider. This is only applicable with MQTT over SSL and MQTT over WebSocket Secure.

Username: Enter the username that the client will use to access the server.

Password: Enter a password for the username.

Client ID: Enter a client ID. The client identifier is sent to the server when the client connects to it.



AXIS Q6088-E PTZ Camera - User manual

HTTP proxy: A URL with a maximum length of 255 bytes. You can leave the field empty if you don't want to use an HTTP proxy.

HTTPS proxy: A URL with a maximum length of 255 bytes. You can leave the field empty if you don't want to use an HTTPS proxy.

Keep alive interval: Enables the client to detect when the server is no longer available without having to wait for the long TCP/IP timeout.

Timeout: The time interval in seconds to allow a connect to complete. Default value: 60

Device topic prefix: Used in the default values for the topic in the connect message and LWT message on the **MQTT client** tab, and in the publication conditions on the **MQTT publication** tab.

Reconnect automatically: Specifies whether the client should reconnect automatically after a disconnect.

Connect message

Specifies if a message should be sent out when a connection is established.

Send message: Turn on to send messages.

Use default: Turn off to enter your own default message.

Topic: Enter the topic for the default message.



AXIS Q6088-E PTZ Camera - User manual

QoS: Change the QoS layer for the packet flow.

Last Will and Testament message

The Last Will Testament (LWT) lets a client provide a testament along with its credentials when connecting to the broker. If the client disconnects ungracefully at some point later (maybe because his power source died), it can let the broker deliver a message to other clients. This LWT message has the same form as an ordinary message and gets routed via the same mechanics.

Send message: Turn on to send messages.

Use default: Turn off to enter your own default message.

Topic: Enter the topic for the default message.

Payload: Enter the content for the default message.

Retain: Select to keep the state of client on this **Topic**

QoS: Change the QoS layer for the packet flow.

MQTT publication

Use default topic prefix: Select to use the default topic prefix, that is defined in the device topic prefix in the **MQTT client** tab.



AXIS Q6088-E PTZ Camera - User manual

ONVIF topic namespaces in the MQTT topic.

Include serial number: Select to include the device's serial number in the MQTT payload.

Add condition: Click to add a condition.

Retain: Defines which MQTT messages are sent as retained.

None: Send all messages as non-retained.

Property: Send only stateful messages as retained.

All: Send both stateful and stateless messages as retained.

QoS: Select the desired level for the MQTT publication.

MQTT subscriptions

Add subscription: Click to add a new



AXIS Q6088-E PTZ Camera - User manual

Use device topic prefix: Add the subscription filter as prefix to the MQTT topic.

Subscription type:

Stateless: Select to convert MQTT messages into a stateless message.

Stateful: Select to convert MQTT messages into a condition. The payload is used as the state.

QoS: Select the desired level for the MQTT subscription.

MQTT overlays

Note

Connect to an MQTT broker before you add MQTT overlay modifiers.

Add overlay modifier: Click to add a new overlay modifier.

Topic filter: Add the MQTT topic that contains the data you want to show in the overlay.

Data field: Specify the key for the message payload that you want to show in



AXIS Q6088-E PTZ Camera - User manual

Modifiers that start with **#XMP** show all of the data received from the topic.

Modifiers that start with **#XMD** show the data specified in the data field.

Storage

Network storage

Network storage: Turn on to use network storage.

Add network storage: Click to add a network share where you can save recordings.

Address: Enter the IP address or host name of the host server, typically a NAS (network-attached storage). We recommend you to configure the host to use a fixed IP address (not DHCP since a dynamic IP address can change) or that you use DNS. Windows SMB/CIFS names are not supported.

Network share: Enter the name of the shared location on the host server. Several Axis devices can use the same network share since each device gets its own folder.

User: If the server requires a login, enter the username. To log in to a specific domain server, type DOMAIN\username.



AXIS Q6088-E PTZ Camera - User manual

NAS. If you select **Auto**, the device tries to negotiate one of the secure versions SMB: 3.02, 3.0, or 2.1. Select 1.0 or 2.0 to connect to older NAS that don't support higher versions. You can read more about SMB support in Axis devices [here](#).

Add share without testing: Select to add the network share even if an error is discovered during the connection test. The error can be, for example, that you didn't enter a password even though the server requires one.

Remove network storage: Click to unmount, unbind, and remove the connection to the network share. This removes all settings for the network share.

Unbind: Click to unbind and disconnect the network share.

Bind: Click to bind and connect the network share.

Unmount: Click to unmount the network share.

Mount: Click to mount the network share.

Write protect: Turn on to stop writing to the network share and protect recordings from being removed. You can't format a write-protected network share.

Retention time: Select how long to keep recordings, to limit the amount of old recordings, or to comply with regulations regarding data storage. If the network storage becomes full, old recordings are



AXIS Q6088-E PTZ Camera - User manual

Test connection: Test the connection to the network share.

Format: Format the network share, for example, when you need to quickly erase all data. CIFS is the available file system option.

Use tool: Click to activate the selected tool.

Onboard storage

Important

Risk of data loss and corrupted recordings. Do not remove the SD card while the device is running. Unmount the SD card before you remove it.

Unmount: Click to safely remove the SD card.

Write protect: Turn on to stop writing to the SD card and protect recordings from being removed. You can't format a write-protected SD card.

Autoformat: Turn on to automatically format a newly inserted SD card. It formats the file system into ext4.

Ignore: Turn on to stop storing recordings on the SD card. When you ignore the SD card, the device no longer recognizes that the card exists. The setting is only available to administrators.



AXIS Q6088-E PTZ Camera - User manual

retention time has passed.

Tools

Check: Check for errors on the SD card.

Repair: Repair errors in the file system.

Format: Format the SD card to change the file system and erase all data. You can only format the SD card to the ext4 file system. You need a third-party ext4 driver or application to access the file system from Windows®.

Encrypt: Use this tool to format the SD card and enable encryption. This erases all data stored on the SD card. Any new data you store on the SD card will be encrypted.

Decrypt: Use this tool to format the SD card without encryption. This erases all data stored on the SD card. Any new data you store on the SD card will not be encrypted.

Change password: Change the password required to encrypt the SD card.

Use tool: Click to activate the selected tool.

Wear trigger: Set a value for the SD card wear level at which you want to trigger an action. The wear level ranges from 0–200%. A new SD card that has never been used has a wear level of 0%. A wear level



AXIS Q6088-E PTZ Camera - User manual

between 80–90%. This gives you time to download any recordings as well as replace the SD card in time before it potentially wears out. The wear trigger allows you to set up an event and get a notification when the wear level reaches your set value.

Stream profiles

A stream profile is a group of settings that affect the video stream. You can use stream profiles in different situations, for example, when you create events and use rules to record.

Add stream profile: Click to create a new stream profile.

Preview: A preview of the video stream with the stream profile settings you select. The preview updates when you change the settings on the page. If your device has different view areas, you can change the view area in the drop-down in the bottom left corner of the image.

Name: Add a name for your profile.

Description: Add a description of your profile.



AXIS Q6088-E PTZ Camera - User manual

Frame rate: See [Stream](#) for a description of this setting.

Compression: See [Stream](#) for a description of this setting.

Zipstream

:

See [Stream](#) for a description of this setting.

Optimize for storage

:

See [Stream](#) for a description of this setting.

Dynamic FPS

:

See [Stream](#) for a description of this setting.



AXIS Q6088-E PTZ Camera - User manual

See [Stream](#) for a description of this setting.

Mirror

:

See [Stream](#) for a description of this setting.

GOP length

:

See [Stream](#) for a description of this setting.

Bitrate control: See [Stream](#) for a description of this setting.

Include overlays

:

Select what type of overlays to include.
See [Overlays](#) for information about how to add overlays.



AXIS Q6088-E PTZ Camera - User manual

See [Stream](#) for a description of this setting.

ONVIF

ONVIF accounts

ONVIF (Open Network Video Interface Forum) is a global interface standard that makes it easier for end-users, integrators, consultants, and manufacturers to take advantage of the possibilities offered by network video technology. ONVIF enables interoperability between different vendor products, increased flexibility, reduced cost and future-proof systems.

When you create an ONVIF account, you automatically enable ONVIF communication. Use the account name and password for all ONVIF communication with the device. For more information see the Axis Developer Community at axis.com.

Add accounts: Click to add a new ONVIF account.

Account: Enter a unique account name.



AXIS Q6088-E PTZ Camera - User manual

numbers, punctuation, and some symbols.

Repeat password: Enter the same password again.

Privileges:

Administrator: Has full access to all settings. Administrators can also add, update, and remove other accounts.

Operator: Has access to all settings except:

- All **System** settings.

- Adding apps.

Media account: Allows access to the video stream only.

The context menu contains:

Update account: Edit the account properties.

Delete account: Delete the account. You can't delete the root account.

ONVIF media profiles

An ONVIF media profile consists of a set of configurations that you can use to change



AXIS Q6088-E PTZ Camera - User manual

Add media profile: Click to add a new ONVIF media profile.

Profile name: Add a name for the media profile.

Video source: Select the video source for your configuration.

Select configuration: Select a user-defined configuration from the list. The configurations in the drop-down list correspond to the device's video channels, including multiviews, view areas and virtual channels.

Video encoder: Select the video encoding format for your configuration.

Select configuration: Select a user-defined configuration from the list and adjust the encoding settings. The configurations in the drop-down list act as identifiers/names of the video encoder configuration. Select user 0 to 15 to apply your own settings, or select one of the default users if you want to use predefined settings for a specific encoding format.

Note



AXIS Q6088-E PTZ Camera - User manual

Audio source

:

Select the audio input source for your configuration.

Select configuration: Select a user-defined configuration from the list and adjust the audio settings. The configurations in the drop-down list correspond to the device's audio inputs. If the device has one audio input, it's user0. If the device has several audio inputs, there will be additional users in the list.

Audio encoder

:

Select the audio encoding format for your configuration.

Select configuration: Select a user-defined configuration from the list and adjust the audio encoding settings. The configurations in the drop-down list act as identifiers/names of the audio encoder configuration.



AXIS Q6088-E PTZ Camera - User manual

Select the audio decoding format for your configuration.

Select configuration: Select a user-defined configuration from the list and adjust the settings. The configurations in the drop-down list act as identifiers/names of the configuration.

Audio output

:

Select the audio output format for your configuration.

Select configuration: Select a user-defined configuration from the list and adjust the settings. The configurations in the drop-down list act as identifiers/names of the configuration.

Metadata: Select the metadata to include in your configuration.

Select configuration: Select a user-defined configuration from the list and adjust the metadata settings. The configurations in the drop-down list act as identifiers/names of the metadata configuration.



AXIS Q6088-E PTZ Camera - User manual

Select the PTZ settings for your configuration.

Select configuration: Select a user-defined configuration from the list and adjust the PTZ settings. The configurations in the drop-down list correspond to the device's video channels with PTZ support.

Create: Click to save your settings and create the profile.

Cancel: Click to cancel the configuration and clear all settings.

profile_x: Click on the profile name to open and edit the preconfigured profile.

Detectors

Shock detection

Shock detector: Turn on to generate an alarm if the device is hit by an object or if it is tampered with.

Sensitivity level: Move the slider to adjust the sensitivity level at which the device should generate an alarm. A low value means that the device only generates an alarm if the hit is powerful. A high value means that the device generates an alarm even with mild tampering.



AXIS Q6088-E PTZ Camera - User manual

Shows power status information.
Information varies depending on the product.

Power profiles

Select a power profile according to the temperature range that the device will be used in:

Full power (default): Select when there's a risk of colder temperatures and ice formation. This is when heaters are used, and power consumption is high.

Cold climate

: Select when there's a risk of colder temperatures and ice formation. Improved pan heater performance, which activates after a device restart. Power consumption is high while the heaters are in use.

Low power: Select to reduce power consumption. The heater is turned off.

Power settings



AXIS Q6088-E PTZ Camera - User manual

Turn on if you want to set a delay time before the power turns off.

Delay time

:

Set a delay time between 1 and 60 minutes.

Power saving mode

:

Turn on to put the device into power saving mode. When you turn on power saving mode, the IR illumination range reduces.

Set power configuration

:

Change the power configuration by selecting a different PoE class option. Click **Save and restart** to save the change.



AXIS Q6088-E PTZ Camera - User manual

device has that option.

Dynamic power mode

:

Turn on to reduce power consumption when the device is inactive.

Power warning overlay

:

Turn on to show a power warning overlay when the device doesn't have enough power.

I/O port power

:

Turn on to supply 12 V power to external devices connected to the I/O ports. Leave off to prioritize internal functions, such as IR, heating, and cooling. As a result, devices and sensors that require 12 V power will stop working properly.



AXIS Q6088-E PTZ Camera - User manual

Shows the current power usage, average power usage, maximum power usage, and power consumption over time.

The context menu contains:

Export: Click to export the chart data.

Edge-to-edge

Pairing

Pairing allows you to use a compatible Axis device as if it were part of the main device.

Add: Add a device to pair with.

Discover devices: Click to find devices on the network. When the network has been scanned a list of available devices is shown.

Note

The list will show all Axis devices that are found, not only devices that can



AXIS Q6088-E PTZ Camera - User manual

interface and go to **System > Network > Network discovery protocols**.

Note

An info icon is shown for devices that have already been paired. Hover over the icon to get information about pairings that are already active.

Audio pairing allows you to pair with network speaker or microphone. Once paired, the network speaker acts as an audio out device where you can play audio clips and transmit sound through the camera. The network microphone will take up sounds from the surrounding area and make it available as an audio input device, usable in media streams and recordings.

Important

For this feature to work with a video management software (VMS), you must first pair the camera with the speaker or microphone, then add the camera to your VMS.

Set a 'Wait between actions (hh:mm:ss)' limit in the event rule when you use a network paired audio device in an event rule with 'Audio detection' as condition and 'Play audio clip' as action. This will help you avoid a looping detection if the



AXIS Q6088-E PTZ Camera - User manual

To pair a device from the list, click

.

Select pairing type: Select from the drop-down list.

Speaker pairing: Select to pair a network speaker.

Microphone pairing

:

Select to pair a microphone.

Address: Enter host name or IP address to the network speaker.

Username: Enter username.

Password: Enter password for the user.

Close: Click to clear all fields.

Connect: Click to establish connection to the device to pair with.

Radar pairing allows you to pair a camera with a compatible Axis radar, and use the camera to configure both devices.



AXIS Q6088-E PTZ Camera - User manual

Select pairing type: Select from the drop-down list.

Address: Enter the host name or IP address of the radar.

Username: Enter the username of the radar.

Password: Enter the password for the radar.

Close: Click to clear all fields.

Connect: Click to connect to the radar.

When connected, the radar settings will be available in the main menu. For more information about radar settings, see the paired radar's user manual.

Logs

Reports and logs

Reports

View the device server report: View information about the product status in a pop-up window. The Access Log is automatically included in the Server Report.

Download the device server report: It creates a .zip file that contains a complete server report text file in



AXIS Q6088-E PTZ Camera - User manual

Download the crash report:

Download an archive with detailed information about the server's status. The crash report contains information that is in the server report as well as detailed debug information. This report might contain sensitive information such as network traces. It can take several minutes to generate the report.

Logs

View the system log: Click to show information about system events such as device startup, warnings, and critical messages.

View the access log: Click to show all failed attempts to access the device, for example, when a wrong login password is used.

View the audit log: Click to show information about user and system activities, for example, successful or failed authentications and configurations.

Remote system log

Syslog is a standard for message logging. It allows separation of the software that generates messages, the system that stores them, and the software that reports and analyzes them. Each message is labeled with a facility code, which indicates the software type generating the message, and assigned a severity level.



AXIS Q6088-E PTZ Camera - User manual

Server: Click to add a new server.

Host: Enter the hostname or IP address of the server.

Format: Select which syslog message format to use.

Axis

RFC 3164

RFC 5424

Protocol: Select the protocol to use:

UDP (Default port is 514)

TCP (Default port is 601)

TLS (Default port is 6514)

Port: Edit the port number to use a different port.

Severity: Select which messages to send when triggered.

Type: Select the type of logs you want to send.

Test server setup: Send a test message to all servers before you save the settings.

CA certificate set: See the current settings or add a certificate.

Plain config



AXIS Q6088-E PTZ Camera - User manual

Maintenance

Maintenance

Restart: Restart the device. This does not affect any of the current settings. Running applications restart automatically.

Restore: Return *most* settings to the factory default values. Afterwards you must reconfigure the device and apps, reinstall any apps that didn't come preinstalled, and recreate any events and presets.

Important

The only settings saved after restore are:

- Boot protocol (DHCP or static)
- Static IP address
- Default router
- Subnet mask
- 802.1X settings
- O3C settings
- DNS server IP address

Factory default: Return *all* settings to the factory default values. Afterwards you must reset the IP address to make the device accessible.

Note



AXIS Q6088-E PTZ Camera - User manual

minimum cybersecurity level of Axis devices. For more information, see the white paper “Axis Edge Vault” at axis.com.

AXIS OS upgrade: Upgrade to a new AXIS OS version. New releases can contain improved functionality, bug fixes, and completely new features. We recommend you to always use the latest AXIS OS release. To download the latest release, go to axis.com/support.

When you upgrade, you can choose between three options:

Standard upgrade: Upgrade to the new AXIS OS version.

Factory default: Upgrade and return all settings to the factory default values. When you choose this option, you can't revert to the previous AXIS OS version after the upgrade.

Automatic rollback: Upgrade and confirm the upgrade within the set time. If you don't confirm, the device reverts to the previous AXIS OS version.

AXIS OS rollback: Revert to the previously installed AXIS OS version.

Troubleshoot



AXIS Q6088-E PTZ Camera - User manual

Reset PTR if for some reason the **Pan**, **Tilt**, or **Roll** settings aren't working as expected. The PTR motors are always calibrated in a new camera. But calibration can be lost, for example, if the camera loses power or if the motors are moved by hand. When you reset PTR, the camera is re-calibrated and returns to its factory default position.

Calibration

:

Click **Calibrate** to recalibrate the pan, tilt, and roll motors to their default positions.

Ping: To check if the device can reach a specific address, enter the hostname or IP address of the host you want to ping and click **Start**.

Port check: To verify connectivity from the device to a specific IP address and TCP/UDP port, enter the hostname or IP address and port number you want to check and click **Start**.

Network trace

Important

A network trace file might contain sensitive information such as



AXIS Q6088-E PTZ Camera - User manual

activity on the network.

Trace time: Select the duration of the trace in seconds or minutes and click **Download**.

Learn more

Laser focus

With laser focus, a laser assists in focusing by providing a reference point. It helps cameras find focus faster than cameras that have autofocus. It finds focus in challenging lighting conditions, such as scenes with low light or contrast. You get the best focus in the center of the image.

The focus performance depends on the weather conditions, the cleanness of the dome, and the reflection value of the object. For example, a mirror or a window can distract the laser. In situations with insufficient object reflections, the camera only uses the autofocus.



With moving objects and scenes that change quickly, laser focus finds focus instantly, making it possible to focus, for example, on the license plate of a moving vehicle.



AXIS Q6088-E PTZ Camera - User manual

Capture modes

A capture mode is a preset configuration that defines how the camera captures images.

The capture mode setting can affect the maximum resolution and maximum frame rate available in the device.

The capture mode with a lower resolution than the maximum can reduce the field of view.

The capture mode also affects the shutter speed, which in turn affects the light sensitivity. This is because a capture mode with a high maximum frame rate has a reduced light sensitivity, and the other way around.

With some capture modes you can't use WDR.

The lower resolution capture mode might be sampled from the original resolution, or it might be cropped out from the original, in which case the field of view could also be affected.

The image shows how the field of view and aspect ratio can change between two different capture modes.

What capture mode to choose depends on the requirements for the frame rate and



AXIS Q6088-E PTZ Camera - User manual

Privacy masks

A privacy mask is a user-defined area that covers part of the monitored area. In the video stream, privacy masks can appear as blocks of solid color, mosaic patterns, or in chameleon mode, which dynamically adapts to the scene to enhance privacy protection.

You'll see the privacy mask on all snapshots, recorded video, and live streams.

You can use the VAPIX® application programming interface (API) to hide the privacy masks.

Important

If you use multiple privacy masks it may affect the product's performance.

You can create several privacy masks. Each mask can have 3 to 10 anchor points.

Overlays

Overlays are superimposed over the video stream. They are used to provide extra information during recordings, such as a timestamp, or during product installation and configuration. You can add either text or an image.

Pan, tilt, and zoom (PTZ)

Guard tours



AXIS Q6088-E PTZ Camera - User manual

guard tour continues to run until stopped, even when there are no clients (web browsers) viewing the images.

The guard tour function includes tour recording. This allows recording a custom tour using an input device, such as a joystick, a mouse, or a keyboard, or through using the VAPIX® Application Programming Interface (API). A recorded tour is a replay of a recorded sequence of pan/tilt/zoom movements, including their variable speeds and lengths.

Streaming and storage

Video compression formats

Decide which compression method to use based on your viewing requirements, and on the properties of your network. The available options are:

Motion JPEG

Motion JPEG, or MJPEG, is a digital video sequence that is made up of a series of individual JPEG images. These images are then displayed and updated at a rate sufficient to create a stream that shows constantly updated motion. For the viewer to perceive motion video the rate must be at least 16 image frames per second. Full motion video is perceived at 30 (NTSC) or 25 (PAL) frames per second.

The Motion JPEG stream uses considerable amounts of bandwidth, but provides excellent image quality and access to every image contained in the stream.



AXIS Q6088-E PTZ Camera - User manual

product includes one H.264 viewing client license. To install additional unlicensed copies of the client is prohibited. To purchase additional licenses, contact your Axis reseller.

H.264 can, without compromising image quality, reduce the size of a digital video file by more than 80% compared to the Motion JPEG format and by as much as 50% compared to older MPEG formats. This means that less network bandwidth and storage space are required for a video file. Or seen another way, higher video quality can be achieved for a given bitrate.

H.265 or MPEG-H Part 2/HEVC

H.265 can, without compromising image quality, reduce the size of a digital video file by more than 25% compared to H.264.

Note

H.265 is licensed technology. The Axis product includes one H.265 viewing client license. Installing additional unlicensed copies of the client is prohibited. To purchase additional licenses, contact your Axis reseller.

Most web browsers don't support H.265 decoding and because of this the camera doesn't support it in its web interface. Instead you can use a video management system or application supporting H.265 decoding.



AXIS Q6088-E PTZ Camera - User manual

streaming even in bandwidth-constrained environments. By reducing a video's bitrate, AV1 preserves video quality while minimizing data usage.

AV1 supports all major browsers, computer operating systems and mobile platforms.

Note

AV1 requires more processing power for encoding and decoding compared to some other codecs.

How do Image, Stream, and Stream profile settings relate to each other?

The **Image** tab contains camera settings that affect all video streams from the product. If you change something in this tab, it immediately affects all video streams and recordings.

The **Stream** tab contains settings for video streams. You get these settings if you request a video stream from the product and don't specify for example resolution, or frame rate. When you change the settings in the **Stream** tab, it doesn't affect ongoing streams, but it will take effect when you start a new stream.

The **Stream profiles** settings override the settings from the **Stream** tab. If you request a stream with a specific stream profile, the stream contains the settings of that profile. If you request a stream without specifying a stream profile, or request a stream profile



AXIS Q6088-E PTZ Camera - User manual

Bitrate control helps you to manage the bandwidth consumption of your video stream.

Variable bitrate (VBR)

Variable bitrate allows the bandwidth consumption to vary depending on the level of activity in the scene. The more activity, the more bandwidth you need. With variable bitrate you are guaranteed constant image quality, but you need to make sure you have storage margins.

Maximum bitrate (MBR)

Maximum bitrate lets you set a target bitrate to handle bitrate limitations in your system. You might see a decline in image quality or frame rate as the instantaneous bitrate is kept below the specified target bitrate. You can choose to prioritize either image quality or frame rate. We recommend that you configure the target bitrate to a higher value than the expected bitrate. This gives you a margin in case there is a high level of activity in the scene.



AXIS Q6088-E PTZ Camera - User manual

of time. This is so you can meet the specified target and provide the best video quality based on your available storage. Bitrate is higher in scenes with a lot of activity, compared to static scenes. You are more likely to get better image quality when in scenes with a lot of activity if you use the average bitrate option. You can define the total storage required to store the video stream for a specified amount of time (retention time) when image quality is adjusted to meet the specified target bitrate. Specify the average bitrate settings in one of the following ways:

To calculate the estimated storage need, set the target bitrate and the retention time.

To calculate the average bitrate, based on available storage and required retention time, use the target bitrate calculator.

1. Target bitrate
2. Actual average bitrate

You can also turn on maximum bitrate and specify a target bitrate within the average bitrate option.



AXIS Q6088-E PTZ Camera - User manual

1. Target bitrate
2. Actual average bitrate

Edge-to-edge technology

Edge-to-edge is a technology that makes IP devices communicate directly with each other. It offers smart pairing functionality between, for example, Axis cameras and Axis audio or radar products.

For more information, see the white paper "Edge-to-edge technology" at whitepapers.axis.com/edge-to-edge-technology.

Speaker pairing

Edge-to-edge speaker pairing allows you to use a compatible Axis network speaker as if it's part of your camera. Once paired, the speaker's features are integrated in the camera's web interface and the network speaker acts as an audio out device where you can play audio clips and transmit sound through the camera.

The camera will identify itself to the VMS as a camera with integrated audio output and redirect any played audio to the speaker.

Radar pairing

With edge-to-edge radar pairing, you can connect your camera to a compatible Axis radar and benefit from integrated radar features, such as speed detection.



AXIS Q6088-E PTZ Camera - User manual

specific events directly in the camera's web interface. The camera will also identify itself to a VMS as a camera with integrated radar functionality.

The camera has an allocated channel for the radar stream, and after pairing, the radar stream will be assigned automatically to this channel.

Additionally, the radar metadata is available through the camera's metadata producer channels after pairing. If the camera in itself has one channel, the radar metadata is available through the second channel.

Analytics and apps

With analytics and apps you can get more out of your Axis device. AXIS Camera Application Platform (ACAP) is an open platform that makes it possible for third parties to develop analytics and other apps for Axis devices. Apps can be preinstalled on the device, available for download for free, or for a license fee.

To find the user manuals for Axis analytics and apps, go to help.axis.com.

Note

Several apps can run at the same time but some apps might not be compatible with each other. Certain combinations of apps might require too much processing power or memory resources when run in parallel.



AXIS Q6088-E PTZ Camera - User manual

With autotracking, the camera automatically zooms in on and tracks moving objects, for example a vehicle or a person. You can manually select an object to track, or connect to an AXIS Object Analytics scenario that triggers automatic tracking of moving objects. The application is best suited for open areas with no obscuring objects and where movement is uncommon. When the camera doesn't track an object, it returns to its connected preset position.

Tracking profiles make it possible to create multiple configurations. Different profiles can for example be connected to different preset positions. You can create up to 10 tracking profiles.

Important

Autotracking is designed for areas with a limited amount of movement.

If both autotracking and guard tour are enabled, autotracking takes priority over guard tour. Guard tour resumes when autotracking stops.

AXIS Object Analytics

AXIS Object Analytics is an analytic application that comes preinstalled on the camera. It detects objects that move in the scene and classifies them as, for example, humans or vehicles. You can set up the application to send alarms for different types of objects. To find out more about how



AXIS Q6088-E PTZ Camera - User manual

AXIS Image Health Analytics is an AI-based application that can be used to detect image degradations or tampering attempts. The application analyzes and learns the behavior of the scene to detect blurriness or underexposure in the image, or to detect an obstructed or redirected view. You can set up the application to send events for any of these detections, and trigger actions through the camera's event system or third-party software.

To find out more about how the application works, see [AXIS Image Health Analytics user manual](#).

Product-specific considerations

For PTZ cameras, it's important to consider the following when using AXIS Image Health Analytics:

Movements, like pan, tilt, and zoom movements, causes the application to send events for a redirected image.

Sudden movements can affect the focus of the image and cause the application to send events for a blurred image.

Moving the camera to a scene that differs greatly from the previous position can cause the application to send events for a blocked image.

Metadata visualization

Analytics metadata is available for moving objects in the scene. Supported object classes are visualized in the video stream



AXIS Q6088-E PTZ Camera - User manual

see [AXIS Scene Metadata integration guide](#).

Cybersecurity

For product-specific information about cybersecurity, see the product's datasheet at [axis.com](#).

For in-depth information about cybersecurity in AXIS OS, read the [AXIS OS Hardening guide](#).

Axis security notification service

Axis provides a notification service with information about vulnerability and other security related matters for Axis devices. To receive notifications, you can subscribe at [axis.com/security-notification-service](#).

Vulnerability management

To minimize customers' risk of exposure, Axis, as a **Common Vulnerability and Exposures (CVE) numbering authority (CNA)**, follows industry standards to manage and respond to discovered vulnerabilities in our devices, software, and services. For more information about Axis vulnerability management policy, how to report vulnerabilities, already disclosed vulnerabilities, and corresponding security advisories, see [axis.com/vulnerability-management](#).

Secure operation of Axis devices

Axis devices with factory default settings are pre-configured with secure default protection mechanisms. We recommend



AXIS Q6088-E PTZ Camera - User manual

<https://www.axis.com/about-axis/cybersecurity>.

Specifications

Product overview

- 1. Power button
- 2. Heater
- 3. Laser
- 4. Status LED
- 5. SD card slot
- 6. Control button
- 7. Unit holder (3x)
- 8. Hook for safety wire
- 9. Network connector
- 10. Ground screw

LED indicators

Status LED	Indication
Unlit	Connection and normal operation.



AXIS Q6088-E PTZ Camera - User manual

	completed.
Amber	Steady during startup. Flashes during device software upgrade or reset to factory default.
Amber/Red	Flashes amber/red if network connection is unavailable or lost.

SD card slot

NOTICE

Risk of damage to SD card. Don't use sharp tools, metal objects, or excessive force when inserting or removing the SD card. Use your fingers to insert and remove the card.

Risk of data loss and corrupted recordings. Unmount the SD card from the device's web interface before removing it. Don't remove the SD card while the product is running.

This device supports SD/SDHC/SDXC cards.

For SD card recommendations, see axis.com.



AXIS Q6088-E PTZ Camera - User manual

United States, other countries or both.

Buttons

Control button

The control button is used for:

Resetting the product to factory default settings. See [Reset to factory default settings](#).

Power button

Press and hold the power button to temporarily power the product when the dome cover is removed.

The power button is also used with the control button to reset the camera to factory default settings. See [Reset to factory default settings](#).

Connectors

Network connector

RJ45 Push-pull Connector (IP66) with High Power over Ethernet (High PoE).

NOTICE

To comply with the IP66-rated design of the camera and maintain the IP66 protection, the supplied RJ45 Push-pull Connector (IP66) shall be used. Alternatively, use the RJ45 IP66-rated cable with premounted connector which is available from your Axis reseller.



AXIS Q6088-E PTZ Camera - User manual

Clean your device

You can clean your device with lukewarm water and mild, nonabrasive soap.

NOTICE

Harsh chemicals can damage the device. Don't use chemicals such as window cleaner or acetone to clean your device.

Don't spray detergent directly on the device. Instead, spray detergent on a nonabrasive cloth and use that to clean the device.

Avoid cleaning in direct sunlight or elevated temperatures, since this can cause stains.

1. Use a can of compressed air to remove dust and loose dirt from the device.
2. If necessary, clean the device with a soft microfiber cloth dampened with lukewarm water and mild, nonabrasive soap.
3. To avoid stains, dry the device with a clean, nonabrasive cloth.

Troubleshooting

Reset to factory default settings

Important



AXIS Q6088-E PTZ Camera - User manual

To reset the product to the factory default settings:

1. Press and hold the control button and the power button for 15–30 seconds until the status LED indicator flashes amber. See [Product overview](#).
2. Release the control button but continue to hold down the power button until the status LED indicator turns green.
3. Release the power button and assemble the product.
4. The process is now complete. The product has been reset to the factory default settings. If no DHCP server is available on the network, the device IP address will default to one of the following:

Devices with AXIS OS 12.0 and later: Obtained from the link-local address subnet (169.254.0.0/16)

Devices with AXIS OS 11.11 and earlier: 192.168.0.90/24

5. Using the installation and management software tools to assign an IP address, set the password and access the video stream.

You can also reset parameters to factory default through the device's web interface. Go to **Maintenance > Factory default** and click **Default**.

AXIS OS options



AXIS Q6088-E PTZ Camera - User manual

while the LTS tracks provide a fixed platform with periodic releases focused mainly on bug fixes and security updates.

Using AXIS OS from the active track is recommended if you want to access the newest features, or if you use Axis end-to-end system offerings. The LTS tracks are recommended if you use third-party integrations, which are not continuously validated against the latest active track. With LTS, the products can maintain cybersecurity without introducing any significant functional changes or affecting any existing integrations. For more detailed information about Axis device software strategy, go to axis.com/support/device-software.

Check the current AXIS OS version

AXIS OS determines the functionality of our devices. When you troubleshoot a problem, we recommend that you to start by checking the current AXIS OS version. The latest version might contain a correction that fixes your particular problem.

To check the current AXIS OS version:

1. Go to the device's web interface > **Status**.
2. Under **Device info**, see the AXIS OS version.

Upgrade AXIS OS

Important



AXIS Q6088-E PTZ Camera - User manual

available in the new AXIS OS) although this is not guaranteed by Axis Communications AB.

Make sure the device remains connected to the power source throughout the upgrade process.

Make sure the cover is attached during upgrade to avoid installation failure.

Note

When you upgrade the device with the latest AXIS OS version in the active track, the product receives the latest functionality available. Always read the upgrade instructions and release notes available with each new release before you upgrade. To find the latest AXIS OS version and the release notes, go to axis.com/support/device-software.

1. Download the AXIS OS file to your computer, available free of charge at axis.com/support/device-software.
2. Log in to the device as an administrator.
3. Go to **Maintenance > AXIS OS upgrade** and click **Upgrade**.

When the upgrade has finished, the product restarts automatically.

You can use AXIS Device Manager to upgrade multiple devices at the same time. Find out more at axis.com/products/axis-device-manager.



AXIS Q6088-E PTZ Camera - User manual

AXIS OS upgrade failed

If the upgrade fails, the device reloads the previous version. The most common reason is that the wrong AXIS OS file has been uploaded. Check that the name of the AXIS OS file corresponds to your device and try again.

Problems after AXIS OS upgrade

If you experience problems after the upgrade, roll back to the previously installed version from the **Maintenance** page.

Problems setting the IP address

Can't set the IP address

If the IP address intended for the device and the IP address of the computer used to access the device are located on different subnets, you can't set the IP address. Contact your network administrator to obtain an IP address.

The IP address could be in use by another device. To check:

1. Disconnect the Axis device from the network.
2. In a Command/DOS window, type `ping` and the IP address of the device.



AXIS Q6088-E PTZ Camera - User manual

device on the network. Obtain a new IP address from the network administrator and reinstall the device.

4. If you receive: Request timed out, this means that the IP address is available for use with the Axis device. Check all cabling and reinstall the device.

There could be a possible IP address conflict with another device on the same subnet. The static IP address in the Axis device is used before the DHCP server sets a dynamic address. This means that if the same default static IP address is also used by another device, there could be problems accessing the device.

Problems accessing the device

Can't log in when accessing the device from a browser

When HTTPS is enabled, make sure that you use the correct protocol (HTTP or HTTPS) when you try to log in. You might need to manually type `http` or `https` in the browser's address field.

If you've lost the password for the root account, you must reset the device to the factory default settings. For instructions, see [Reset to factory default settings](#).

The IP address has been changed by DHCP



AXIS Q6088-E PTZ Camera - User manual

device using its model or serial number, or by the DNS name (if the name has been configured).

If required, you can assign a static IP address manually. For instructions, go to axis.com/support.

Certificate error when using IEEE 802.1X

For authentication to work properly, the date and time settings in the Axis device must be synchronized with an NTP server. Go to **System > Date and time**.

The browser isn't supported

For a list of recommended browsers, see [Browser support](https://axis.com/support).

Can't access the device externally

To access the device externally, we recommend you to use one of the following applications for Windows®:

AXIS Camera Station Edge: free of charge, ideal for small systems with basic surveillance needs.

AXIS Camera Station 5: 30-day trial version free of charge, ideal for small to mid-size systems.

AXIS Camera Station Pro: 90-day trial version free of charge, ideal for small to mid-size systems.



AXIS Q6088-E PTZ Camera - User manual

Multicast H.264 only accessible by local clients

Check if your router supports multicasting, or if you need to configure the router settings between the client and the device. You might need to increase the TTL (Time To Live) value.

No multicast H.264 displayed in the client

Check with your network administrator that the multicast addresses used by the Axis device are valid for your network.

Check with your network administrator to see if there is a firewall that prevents viewing.

Poor rendering of H.264 images

Ensure that your graphics card uses the latest driver. You can usually download the latest drivers from the manufacturer's website.

Color saturation is different in H.264 and Motion JPEG

Modify the settings for your graphics adapter. Check the adapter's documentation for more information.

Lower frame rate than expected



AXIS Q6088-E PTZ Camera - User manual

viewers.

Check with the network administrator that there is enough bandwidth available.

Lower the image resolution.

Log in to the device's web interface and set a capture mode that prioritizes frame rate. If you change the capture mode to prioritize frame rate it might lower the maximum resolution, depending on the device used and capture modes available.

The maximum frames per second is dependent on the utility frequency (60/50 Hz) of the Axis device.

Can't select H.265 encoding in live view

Web browsers don't support H.265 decoding. Use a video management system or application that supports H.265 decoding.

Problems with MQTT

Can't connect over port 8883 with MQTT over SSL

The firewall blocks traffic that uses port 8883 since it's regarded insecure.

In some cases the server/broker might not provide a specific port for MQTT communication. It might still be possible to use MQTT over a port normally used for HTTP/HTTPS traffic.



AXIS Q6088-E PTZ Camera - User manual

server/broker provider to see if WS/WSS is supported and which port and basepath to use.

If the server/broker supports ALPN, the use of MQTT can be negotiated over an open port, such as 443. Check with your server/broker provider to see if ALPN is supported and which ALPN protocol and port to use.

If you can't find what you're looking for here, try the troubleshooting section at axis.com/support.

Performance considerations

When you set up your system, it's important to consider how different settings and situations affect performance. Some factors affect bandwidth (bitrate), others affect frame rate, and some affect both.

The most important factors to consider:

High image resolution or lower compression levels result in images containing more data which in turn affects the bandwidth.

Rotating the image in the GUI can increase the product's CPU load.

Removing or attaching the cover will restart the camera.

Access by large numbers of Motion JPEG clients or unicast H.264/H.265/AV1 clients affects the bandwidth.



AXIS Q6088-E PTZ Camera - User manual

Use identical streams wherever possible to maintain a high frame rate. Stream profiles can be used to ensure that streams are identical.

Accessing video streams with different codecs simultaneously affects both frame rate and bandwidth. For optimal performance, use streams with the same codec.

Heavy usage of event settings affects the product's CPU load which in turn affects the frame rate.

Using HTTPS may reduce frame rate, in particular if streaming Motion JPEG.

Heavy network utilization due to poor infrastructure affects the bandwidth.

Viewing on poorly performing client computers lowers perceived performance and affects frame rate.

Running multiple AXIS Camera Application Platform (ACAP) applications simultaneously may affect the frame rate and the general performance.

Contact support

If you need more help, go to axis.com/support.



AXIS Q6088-E PTZ Camera - User manual
